MJE13005G

SWITCHMODE™ Series NPN Silicon Power Transistors

These devices are designed for high−voltage, high−speed power switching inductive circuits where fall time is critical. They are particularly suited for 115 and 220 V SWITCHMODE applications such as Switching Regulator's, Inverters, Motor Controls, Solenoid/Relay drivers and Deflection circuits.

Features

- $V_{CEO(sus)}$ 400 V
- Reverse Bias SOA with Inductive Loads @ T_C = 100°C
- Inductive Switching Matrix 2 to 4 A, 25 and 100°C t_c @ 3A, 100°C is 180 ns (Typ)
- 700 V Blocking Capability
- SOA and Switching Applications Information
- These Devices are Pb−Free and are RoHS Compliant*

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector−Emitter Voltage	$V_{CEO(sus)}$	400	Vdc
Collector−Emitter Voltage	V_{CEV}	700	Vdc
Emitter−Base Voltage	V_{EBO}	9	Vdc
Collector Current − Continuous − Peak (Note 1)	I_C I_{CM}	4 8	Adc
Base Current − Continuous − Peak (Note 1)	I_B I_{BM}	2 4	Adc
Emitter Current − Continuous − Peak (Note 1)	I_E I_{EM}	6 12	Adc
Total Device Dissipation @ T_A = 25°C Derate above 25°C	P_D	2 0.016	W W/°C
Total Device Dissipation @ T_C = 25°C Derate above 25°C	P_D	75 0.6	W W/°C
Operating and Storage Junction Temperature Range	T_J, T_{stg}	−65 to +150	°C

THERMAL CHARACTERISTICS

Characteristics	Symbol	Max	Unit
Thermal Resistance, Junction−to−Ambient	$R_{\theta JA}$	62.5	°C/W
Thermal Resistance, Junction−to−Case	$R_{\theta JC}$	1.67	°C/W
Maximum Lead Temperature for Soldering Purposes 1/8″ from Case for 5 Seconds	T_L	275	°C

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

1. Pulse Test: Pulse Width = 5 ms, Duty Cycle ≤ 10%.

*For additional information on our Pb−Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor®

http://onsemi.com

4 AMPERE NPN SILICON POWER TRANSISTOR 400 VOLTS − 75 WATTS



TO−220AB
CASE 221A−09
STYLE 1

MARKING DIAGRAM



A = Assembly Location
Y = Year
WW = Work Week
G = Pb−Free Package

ORDERING INFORMATION

Device	Package	Shipping
MJE13005G	TO−220 (Pb−Free)	50 Units / Rail

© Semiconductor Components Industries, LLC, 2010

ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
OFF CHARACTERISTICS (Note 2)					
Collector−Emitter Sustaining Voltage (I_C = 10 mA, I_B = 0)	$V_{CEO(sus)}$	400	–	–	Vdc
Collector Cutoff Current	I_{CEV}				mAdc
(V_{CEV} = Rated Value, $V_{BE(off)}$ = 1.5 Vdc)		–	–	1	
(V_{CEV} = Rated Value, $V_{BE(off)}$ = 1.5 Vdc, T_C = 100°C)		–	–	5	
Emitter Cutoff Current (V_{EB} = 9 Vdc, I_C = 0)	I_{EBO}	–	–	1	mAdc
SECOND BREAKDOWN					
Second Breakdown Collector Current with base forward biased	$I_{S/b}$	–	See Figure 11		
Clamped Inductive SOA with Base Reverse Biased	RBSOA	–	See Figure 12		
ON CHARACTERISTICS (Note 2)					
DC Current Gain	h_{FE}				–
(I_C = 1 Adc, V_{CE} = 5 Vdc)		10	–	60	
(I_C = 2 Adc, V_{CE} = 5 Vdc)		8	–	40	
Collector−Emitter Saturation Voltage	$V_{CE(sat)}$				Vdc
(I_C = 1 Adc, I_B = 0.2 Adc)		–	–	0.5	
(I_C = 2 Adc, I_B = 0.5 Adc)		–	–	0.6	
(I_C = 4 Adc, I_B = 1 Adc)		–	–	1	
(I_C = 2 Adc, I_B = 0.5 Adc, T_C = 100°C)		–	–	1	
Base−Emitter Saturation Voltage	$V_{BE(sat)}$				Vdc
(I_C = 1 Adc, I_B = 0.2 Adc)		–	–	1.2	
(I_C = 2 Adc, I_B = 0.5 Adc)		–	–	1.6	
(I_C = 2 Adc, I_B = 0.5 Adc, T_C = 100°C)		–	–	1.5	
DYNAMIC CHARACTERISTICS					
Current−Gain − Bandwidth Product (I_C = 500 mAdc, V_{CE} = 10 Vdc, f = 1 MHz)	f_T	4	–	–	MHz
Output Capacitance (V_{CB} = 10 Vdc, I_E = 0, f = 0.1 MHz)	C_{ob}	–	65	–	pF
SWITCHING CHARACTERISTICS					
Resistive Load (Table 2)					
Delay Time	(V_{CC} = 125 Vdc, I_C = 2 A, I_{B1} = I_{B2} = 0.4 A, t_p = 25 μs, Duty Cycle ≤ 1%)	t_d	–	0.025	0.1	μs
Rise Time		t_r	–	0.3	0.7	μs
Storage Time		t_s	–	1.7	4	μs
Fall Time		t_f	–	0.4	0.9	μs
Inductive Load, Clamped (Table 2, Figure 13)					
Voltage Storage Time	(I_C = 2 A, V_{clamp} = 300 Vdc, I_{B1} = 0.4 A, $V_{BE(off)}$ = 5 Vdc, T_C = 100°C)	t_{sv}	–	0.9	4	μs
Crossover Time		t_c	–	0.32	0.9	μs
Fall Time		t_{fi}	–	0.16	–	μs

2. Pulse Test: Pulse Width = 300 μs, Duty Cycle = 2%.



Figure 1. DC Current Gain



Figure 2. Collector Saturation Region



Figure 3. Base−Emitter Voltage



Figure 4. Collector−Emitter Saturation Voltage



Figure 5. Collector Cutoff Region



Figure 6. Capacitance



Figure 7. Inductive Switching Measurements

Table 1. Typical Inductive Switching Performance

I_C AMP	T_C °C	t_{sv} ns	t_{rv} ns	t_{fi} ns	t_{ti} ns	t_c ns
2	25 100	600 900	70 110	100 240	80 130	180 320
3	25 100	650 950	60 100	140 330	60 100	200 350
4	25 100	550 850	70 110	160 350	100 160	220 390

NOTE: All Data recorded in the inductive Switching Circuit In Table 2.

SWITCHING TIMES NOTE

In resistive switching circuits, rise, fall, and storage times have been defined and apply to both current and voltage waveforms since they are in phase. However, for inductive loads which are common to SWITCHMODE power supplies and hammer drivers, current and voltage waveforms are not in phase. Therefore, separate measurements must be made on each waveform to determine the total switching time. For this reason, the following new terms have been defined.

t_{sv} = Voltage Storage Time, 90% I_{B1} to 10% V_{clamp}

t_{rv} = Voltage Rise Time, 10−90% V_{clamp}

t_{fi} = Current Fall Time, 90−10% I_C

t_{ti} = Current Tail, 10−2% I_C

t_c = Crossover Time, 10% V_{clamp} to 10% I_C

An enlarged portion of the inductive switching waveforms is shown in Figure 7 to aid in the visual identity of these terms.

For the designer, there is minimal switching loss during storage time and the predominant switching power losses occur during the crossover interval and can be obtained using the standard equation from AN−222:

$$P_{SWT} = 1/2\ V_{CC} I_C (t_c) f$$

In general, $t_{rv} + t_{fi} \simeq t_c$. However, at lower test currents this relationship may not be valid.

As is common with most switching transistors, resistive switching is specified at 25°C and has become a benchmark for designers. However, for designers of high frequency converter circuits, the user oriented specifications which make this a “SWITCHMODE” transistor are the inductive switching speeds (t_c and t_{sv}) which are guaranteed at 100°C.

RESISTIVE SWITCHING PERFORMANCE



Figure 8. Turn−On Time



Figure 9. Turn−Off Time

Table 2. Test Conditions for Dynamic Performance

	REVERSE BIAS SAFE OPERATING AREA AND INDUCTIVE SWITCHING	RESISTIVE SWITCHING
TEST CIRCUITS		
CIRCUIT VALUES	Coil Data: Ferroxcube Core #6656 Full Bobbin (~16 Turns) #16 GAP for 200 μH/20 A L_{coil} = 200 μH V_{CC} = 20 V V_{clamp} = 300 Vdc	V_{CC} = 125 V R_C = 62 Ω D1 = 1N5820 or Equiv. R_B = 22 Ω
TEST WAVEFORMS	OUTPUT WAVEFORMS  t_1 ADJUSTED TO OBTAIN I_C $t_1 \approx \frac{L_{coil}(I_{C_{pk}})}{V_{CC}}$ $t_2 \approx \frac{L_{coil}(I_{C_{pk}})}{V_{clamp}}$ Test Equipment Scope–Tektronics 475 or Equivalent	 t_r, t_f < 10 ns Duty Cycle = 1.0% R_B and R_C adjusted for desired I_B and I_C



Figure 10. Typical Thermal Response [$Z_{\theta JC}(t)$]

SAFE OPERATING AREA INFORMATION

The Safe Operating Area Figures 11 and 12 are specified ratings for these devices under the test conditions shown.



Figure 11. Forward Bias Safe Operating Area



Figure 12. Reverse Bias Switching Safe Operating Area

FORWARD BIAS

There are two limitations on the power handling ability of a transistor: average junction temperature and second breakdown. Safe operating area curves indicate $I_C - V_{CE}$ limits of the transistor that must be observed for reliable operation; i.e., the transistor must not be subjected to greater dissipation than the curves indicate.

The data of Figure 11 is based on $T_C = 25°C$; $T_{J(pk)}$ is variable depending on power level. Second breakdown pulse limits are valid for duty cycles to 10% but must be derated when $T_C \ge 25°C$. Second breakdown limitations do not derate the same as thermal limitations. Allowable current at the voltages shown on Figure 11 may be found at any case temperature by using the appropriate curve on Figure 13.

$T_{J(pk)}$ may be calculated from the data in Figure 10. At high case temperatures, thermal limitations will reduce the power that can be handled to values less than the limitations imposed by second breakdown.

REVERSE BIAS

For inductive loads, high voltage and high current must be sustained simultaneously during turn−off, in most cases, with the base to emitter junction reverse biased. Under these conditions the collector voltage must be held to a safe level at or below a specific value of collector current. This can be accomplished by several means such as active clamping, RC snubbing, load line shaping, etc. The safe level for these devices is specified as Reverse Bias Safe Operating Area and represents the voltage−current conditions during reverse biased turn−off. This rating is verified under clamped conditions so that the device is never subjected to an avalanche mode. Figure 12 gives the complete RBSOA characteristics.



Figure 13. Forward Bias Power Derating

SWITCHMODE is a trademark of Semiconductor Components Industries, LLC.

onsemi, ONSEMI , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent−Marking.pdf. **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as−is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:
Technical Library: www.onsemi.com/design/resources/technical−documentation
onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support
For additional information, please contact your local Sales Representative at
www.onsemi.com/support/sales