

# Dual 2-A High-Speed, Low-Side Gate Drivers

## FAN3226, FAN3227, FAN3228, FAN3229

### Description

The FAN3226–29 family of dual 2 A gate drivers is designed to drive N-channel enhancement-mode MOSFETs in low-side switching applications by providing high peak current pulses during the short switching intervals. The driver is available with either TTL or CMOS input thresholds. Internal circuitry provides an under-voltage lockout function by holding the output low until the supply voltage is within the operating range. In addition, the drivers feature matched internal propagation delays between A and B channels for applications requiring dual gate drives with critical timing, such as synchronous rectifiers. This enables connecting two drivers in parallel to effectively double the current capability driving a single MOSFET.

The FAN322X drivers incorporate MillerDrive™ architecture for the final output stage. This bipolar–MOSFET combination provides high current during the Miller plateau stage of the MOSFET turn-on/turn-off process to minimize switching loss, while providing rail-to-rail voltage swing and reverse current capability.

The FAN3226 offers two inverting drivers and the FAN3227 offers two non-inverting drivers. Each device has dual independent enable pins that default to ON if not connected. In the FAN3228 and FAN3229, each channel has dual inputs of opposite polarity, which allows configuration as non-inverting or inverting with an optional enable function using the second input. If one or both inputs are left unconnected, internal resistors bias the inputs such that the output is pulled low to hold the power MOSFET off.

### Features

- Industry–Standard Pinouts
- 4.5–V to 18–V Operating Range
- 3–A Peak Sink/Source at  $V_{DD} = 12\text{ V}$
- 2.4 A–Sink/1.6–A Source at  $V_{OUT} = 6\text{ V}$
- Choice of TTL or CMOS Input Thresholds
- Four Versions of Dual Independent Drivers:
  - ◆ Dual Inverting + Enable (FAN3226)
  - ◆ Dual Non–Inverting + Enable (FAN3227)
  - ◆ Dual Inputs in Two Pin–Out Configurations:
    - Compatible with FAN3225x (FAN3228)
    - Compatible with TPS2814D (FAN3229)
- Internal Resistors Turn Driver Off If No Inputs
- MillerDrive Technology
- 12–ns/9–ns Typical Rise/Fall Times (1–nF Load)
- Under 20–ns Typical Propagation Delay Matched within 1 ns to the Other Channel
- Double Current Capability by Paralleling Channels




ON Semiconductor®

[www.onsemi.com](http://www.onsemi.com)



SOIC8  
CASE 751EB

### MARKING DIAGRAM



\$Y = ON Semiconductor Logo Graphic  
&Z = Assembly Plant Code  
&2 = 2–Digit Data Code (Year & Week)  
&K = 2–Digit Lot Run Traceability Code

(Note: Microdot may be in either location)

### ORDERING INFORMATION

See detailed ordering and shipping information on page 20 of this data sheet.

### Features (Continued)

- 8–Lead SOIC Package
- Rated from –40°C to +125°C Ambient
- AEC–Q100 Qualified and PPAP Capable
- These are Pb–Free Devices

### Applications

- Switch–Mode Power Supplies
- High–Efficiency MOSFET Switching
- Synchronous Rectifier Circuits
- DC–to–DC Converters
- Motor Control
- Servers
- Automotive–Qualified Systems

# FAN3226, FAN3227, FAN3228, FAN3229

## PIN CONFIGURATIONS




Figure 1. Pin Configurations

## PACKAGE OUTLINES




Figure 2. SOIC-8 (Top View)

## THERMAL CHARACTERISTICS (Note 1)

| Package                                       | $\theta_{JL}$<br>(Note 2) | $\theta_{JT}$<br>(Note 3) | $\theta_{JA}$<br>(Note 4) | $\Psi_{JB}$<br>(Note 5) | $\Psi_{JT}$<br>(Note 6) | Unit |
|-----------------------------------------------|---------------------------|---------------------------|---------------------------|-------------------------|-------------------------|------|
| 8-Pin Small Outline Integrated Circuit (SOIC) | 40                        | 31                        | 89                        | 43                      | 3.0                     | °C/W |

1. Estimates derived from thermal simulation; actual values depend on the application.
2.  $\theta_{JL}$  ( $\theta_{JL}$ ): Thermal resistance between the semiconductor junction and the bottom surface of all the leads (including any thermal pad) that are typically soldered to a PCB.
3.  $\theta_{JT}$  ( $\theta_{JT}$ ): Thermal resistance between the semiconductor junction and the top surface of the package, assuming it is held at a uniform temperature by a top-side heatsink.
4.  $\theta_{JA}$  ( $\theta_{JA}$ ): Thermal resistance between junction and ambient, dependent on the PCB design, heat sinking, and airflow. The value given is for natural convection with no heatsink using a 2S2P board, as specified in JEDEC standards JESD51-2, JESD51-5, and JESD51-7, as appropriate.
5.  $\Psi_{JB}$  ( $\Psi_{JB}$ ): Thermal characterization parameter providing correlation between semiconductor junction temperature and an application circuit board reference point for the thermal environment defined in Note 4. For the SOIC-8 package, the board reference is defined as the PCB copper adjacent to pin 6.
6.  $\Psi_{JT}$  ( $\Psi_{JT}$ ): Thermal characterization parameter providing correlation between the semiconductor junction temperature and the center of the top of the package for the thermal environment defined in Note 4.

# FAN3226, FAN3227, FAN3228, FAN3229

## PIN DEFINITIONS

| Name | Description                                                                                                               |
|------|---------------------------------------------------------------------------------------------------------------------------|
| ENA  | Enable Input for Channel A. Pull pin LOW to inhibit driver A. ENA has TTL thresholds for both TTL and CMOS INx threshold. |
| ENB  | Enable Input for Channel B. Pull pin LOW to inhibit driver B. ENB has TTL thresholds for both TTL and CMOS INx threshold. |
| GND  | Ground. Common ground reference for input and output circuits.                                                            |
| INA  | Input to Channel A.                                                                                                       |
| INA+ | Non-Inverting Input to Channel A. Connect to VDD to enable output.                                                        |
| INA- | Inverting Input to Channel A. Connect to GND to enable output.                                                            |
| INB  | Input to Channel B.                                                                                                       |
| INB+ | Non-Inverting Input to Channel B. Connect to VDD to enable output.                                                        |
| INB- | Inverting Input to Channel B. Connect to GND to enable output.                                                            |
| OUTA | Gate Drive Output A: Held LOW unless required input(s) are present and VDD is above UVLO threshold.                       |
| OUTB | Gate Drive Output B: Held LOW unless required input(s) are present and VDD is above UVLO threshold.                       |
| OUTA | Gate Drive Output A (inverted from the input): Held LOW unless required input is present and VDD is above UVLO threshold. |
| OUTB | Gate Drive Output B (inverted from the input): Held LOW unless required input is present and VDD is above UVLO threshold. |
| VDD  | Supply Voltage. Provides power to the IC.                                                                                 |




Figure 3. Pin Configurations (Repeated)

## OUTPUT LOGIC

| FAN3226 (x = A or B) |            |      |
|----------------------|------------|------|
| ENx                  | INx        | OUTx |
| 0                    | 0          | 0    |
| 0                    | 1 (Note 7) | 0    |
| 1 (Note 7)           | 0          | 1    |
| 1 (Note 7)           | 1 (Note 7) | 0    |

| FAN3228 and FAN3229 (x = A or B) |            |      |
|----------------------------------|------------|------|
| INx+                             | INx-       | OUTx |
| 0 (Note 7)                       | 0          | 0    |
| 0 (Note 7)                       | 1 (Note 7) | 0    |
| 1                                | 0          | 1    |
| 1                                | 1 (Note 7) | 0    |

| FAN3227 (x = A or B) |            |      |
|----------------------|------------|------|
| ENx                  | INx        | OUTx |
| 0                    | 0 (Note 7) | 0    |
| 0                    | 1          | 0    |
| 1 (Note 7)           | 0 (Note 7) | 0    |
| 1 (Note 7)           | 1          | 1    |

7. Default input signal if no external connection is made.

# FAN3226, FAN3227, FAN3228, FAN3229

## BLOCK DIAGRAMS




Figure 4. FAN3226 Block Diagram




Figure 5. FAN3227 Block Diagram

# FAN3226, FAN3227, FAN3228, FAN3229




Figure 6. FAN3228 Block Diagram




Figure 7. FAN3229 Block Diagram

# FAN3226, FAN3227, FAN3228, FAN3229

## ABSOLUTE MAXIMUM RATINGS

| Symbol           | Parameter                                  | Min       | Max                   | Unit |
|------------------|--------------------------------------------|-----------|-----------------------|------|
| V <sub>DD</sub>  | VDD to GND                                 | -0.3      | 20.0                  | V    |
| V <sub>EN</sub>  | ENA and ENB to GND                         | GND - 0.3 | V <sub>DD</sub> + 0.3 | V    |
| V <sub>IN</sub>  | INA, INA+, INA-, INB, INB+ and INB- to GND | GND - 0.3 | V <sub>DD</sub> + 0.3 | V    |
| V <sub>OUT</sub> | OUTA and OUTB to GND                       | GND - 0.3 | V <sub>DD</sub> + 0.3 | V    |
| T <sub>L</sub>   | Lead Soldering Temperature (10 Seconds)    | -         | +260                  | °C   |
| T <sub>J</sub>   | Junction Temperature                       | -55       | +150                  | °C   |
| T <sub>STG</sub> | Storage Temperature                        | -65       | +150                  | °C   |

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

## RECOMMENDED OPERATING CONDITIONS

| Symbol          | Parameter                                         | Min | Max             | Unit |
|-----------------|---------------------------------------------------|-----|-----------------|------|
| V <sub>DD</sub> | Supply Voltage Range                              | 4.5 | 18.0            | V    |
| V <sub>EN</sub> | Enable Voltage ENA and ENB                        | 0   | V <sub>DD</sub> | V    |
| V <sub>IN</sub> | Input Voltage INA, INA+, INA-, INB, INB+ and INB- | 0   | V <sub>DD</sub> | V    |
| T <sub>A</sub>  | Operating Ambient Temperature                     | -40 | +125            | °C   |

Functional operation above the stresses listed in the Recommended Operating Ranges is not implied. Extended exposure to stresses beyond the Recommended Operating Ranges limits may affect device reliability.

**ELECTRICAL CHARACTERISTICS** (V<sub>DD</sub> = 12 V and T<sub>J</sub> = -40°C to +125°C unless otherwise noted. Currents are defined as positive into the device and negative out of the device.)

| Symbol | Parameter | Test Condition | Min | Typ | Max | Unit |
|--------|-----------|----------------|-----|-----|-----|------|
|--------|-----------|----------------|-----|-----|-----|------|

### SUPPLY

|                  |                                         |                                                  |     |      |      |    |
|------------------|-----------------------------------------|--------------------------------------------------|-----|------|------|----|
| V <sub>DD</sub>  | Operating Range                         |                                                  | 4.5 | -    | 18.0 | V  |
| I <sub>DD</sub>  | Supply Current, Inputs/EN Not Connected | TTL                                              | -   | 0.75 | 1.20 | mA |
|                  |                                         | CMOS (Note 8)                                    | -   | 0.65 | 1.05 |    |
| V <sub>ON</sub>  | Turn-On Voltage                         | INA = ENA = V <sub>DD</sub> ,<br>INB = ENB = 0 V | 3.3 | 3.9  | 4.5  | V  |
| V <sub>OFF</sub> | Turn-Off Voltage                        | INA = ENA = V <sub>DD</sub> ,<br>INB = ENB = 0 V | 3.1 | 3.7  | 4.3  | V  |

### INPUTS (TTL, FAN322XT) (Note 9)

|                    |                              |                      |      |      |     |    |
|--------------------|------------------------------|----------------------|------|------|-----|----|
| V <sub>INL_T</sub> | INx Logic Low Threshold      |                      | 0.8  | 1.2  | -   | V  |
| V <sub>INH_T</sub> | INx Logic High Threshold     |                      | -    | 1.6  | 2.0 | V  |
| V <sub>HYS_T</sub> | TTL Logic Hysteresis Voltage |                      | 0.2  | 0.4  | 0.8 | V  |
| I <sub>INX_T</sub> | Non-Inverting Input Current  | IN = 0 V             | -1.5 | -    | 1.5 | μA |
| I <sub>INX_T</sub> | Non-Inverting Input Current  | IN = V <sub>DD</sub> | 90   | 120  | 175 | μA |
| I <sub>INX_T</sub> | Inverting Input Current      | IN = 0 V             | -175 | -120 | -90 | μA |
| I <sub>INX_T</sub> | Inverting Input Current      | IN = V <sub>DD</sub> | -1.5 | -    | 1.5 | μA |

### INPUTS (FAN322xC) (Note 9)

|                    |                               |                      |      |     |     |                  |
|--------------------|-------------------------------|----------------------|------|-----|-----|------------------|
| V <sub>INL_C</sub> | INx Logic Low Threshold       |                      | 30   | 38  | -   | %V <sub>DD</sub> |
| V <sub>INH_C</sub> | INx Logic High Threshold      |                      | -    | 55  | 70  | %V <sub>DD</sub> |
| V <sub>HYS_C</sub> | CMOS Logic Hysteresis Voltage |                      | -    | 17  | -   | %V <sub>DD</sub> |
| I <sub>INX_T</sub> | Non-Inverting Input Current   | IN = 0 V             | -1.5 | -   | 1.5 | μA               |
| I <sub>INX_T</sub> | Non-Inverting Input Current   | IN = V <sub>DD</sub> | 90   | 120 | 175 | μA               |

## FAN3226, FAN3227, FAN3228, FAN3229

**ELECTRICAL CHARACTERISTICS** ( $V_{DD} = 12\text{ V}$  and  $T_J = -40^\circ\text{C}$  to  $+125^\circ\text{C}$  unless otherwise noted. Currents are defined as positive into the device and negative out of the device.) (continued)

| Symbol       | Parameter               | Test Condition | Min  | Typ  | Max | Unit          |
|--------------|-------------------------|----------------|------|------|-----|---------------|
| $I_{INX\_T}$ | Inverting Input Current | IN = 0 V       | -175 | -120 | -90 | $\mu\text{A}$ |
| $I_{INX\_T}$ | Inverting Input Current | IN = $V_{DD}$  | -1.5 | -    | 1.5 | $\mu\text{A}$ |

### ENABLE (FAN3226C, FAN3226T, FAN3227C, FAN3227T)

|              |                                          |                                 |     |     |     |           |
|--------------|------------------------------------------|---------------------------------|-----|-----|-----|-----------|
| $V_{ENL}$    | Enable Logic Low Threshold               | EN from 5 V to 0 V              | 0.8 | 1.2 | -   | V         |
| $V_{ENH}$    | Enable Logic High Threshold              | EN from 0 V to 5 V              | -   | 1.6 | 2.0 | V         |
| $V_{HYS\_T}$ | TTL Logic Hysteresis Voltage             |                                 | -   | 0.4 | -   | V         |
| $R_{PU}$     | Enable Pull-up Resistance                |                                 | -   | 100 | -   | $k\Omega$ |
| $t_{D3}$     | EN to Output Propagation Delay (Note 11) | 0 V to 5 V EN, 1 V/ns Slew Rate | 8   | 19  | 35  | ns        |
| $t_{D4}$     |                                          | 5 V to 0 V EN, 1 V/ns Slew Rate | 8   | 18  | 35  | ns        |

### OUTPUTS

|                  |                                              |                                                                              |   |      |    |    |
|------------------|----------------------------------------------|------------------------------------------------------------------------------|---|------|----|----|
| $I_{SINK}$       | OUT Current, Mid-Voltage, Sinking (Note 10)  | OUT at $V_{DD}/2$ , $C_{LOAD} = 0.1\text{ }\mu\text{F}$ , $f = 1\text{ kHz}$ | - | 2.4  | -  | A  |
| $I_{SOURCE}$     | OUT Current, Mid-Voltage, Sourcing (Note 10) | OUT at $V_{DD}/2$ , $C_{LOAD} = 0.1\text{ }\mu\text{F}$ , $f = 1\text{ kHz}$ | - | -1.6 | -  | A  |
| $I_{PK\_SINK}$   | OUT Current, Peak, Sinking (Note 10)         | $C_{LOAD} = 0.1\text{ }\mu\text{F}$ , $f = 1\text{ kHz}$                     | - | 3    | -  | A  |
| $I_{PK\_SOURCE}$ | OUT Current, Peak, Sourcing (Note 10)        | $C_{LOAD} = 0.1\text{ }\mu\text{F}$ , $f = 1\text{ kHz}$                     | - | -3   | -  | A  |
| $t_{RISE}$       | Output Rise Time (Note 11)                   | $C_{LOAD} = 1000\text{ pF}$                                                  | - | 12   | 22 | ns |
| $t_{FALL}$       | Output Fall Time (Note 11)                   | $C_{LOAD} = 1000\text{ pF}$                                                  | - | 9    | 17 | ns |
| $I_{RVS}$        | Output Reverse Current Withstand (Note 10)   |                                                                              | - | 500  | -  | mA |

### FAN322xT, FAN322xC

|                  |                                                 |                                                        |   |    |    |    |
|------------------|-------------------------------------------------|--------------------------------------------------------|---|----|----|----|
| $t_{D1}$         | Output Propagation Delay, CMOS Inputs (Note 12) | CMOS Input                                             | 7 | 15 | 33 | ns |
| $t_{D2}$         |                                                 | CMOS Input                                             | 6 | 15 | 42 | ns |
| $t_{D1}$         | Output Propagation Delay, TTL Inputs (Note 12)  | TTL Input                                              | 9 | 19 | 34 | ns |
| $t_{D2}$         |                                                 | TTL Input                                              | 9 | 18 | 32 | ns |
| $t_{DEL\_MATCH}$ | Propagation Matching Between Channels (Note 12) | INA = INB, OUTA and OUTB at 50% Point                  | - | 2  | 4  | ns |
| $V_{OH}$         | High Level Output Voltage                       | $V_{OH} = V_{DD} - V_{OUT}$ , $I_{OUT} = -1\text{ mA}$ | - | 15 | 35 | mV |
| $V_{OL}$         | Low Level Output Voltage                        | $I_{OUT} = 1\text{ mA}$                                | - | 10 | 25 | mV |

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

8. Lower supply current due to inactive TTL circuitry.

9. EN inputs have modified TTL thresholds; refer to the ENABLE section.

10. Not tested in production.

11. See Timing Diagrams of Figure 10 and Figure 11.

12. See Timing Diagrams of Figure 8 and Figure 9.

TIMING DIAGRAMS




Figure 8. Non-Inverting (EN HIGH or Floating)




Figure 9. Inverting (EN HIGH or Floating)




Figure 10. Non-Inverting (IN HIGH)




Figure 11. Inverting (IN LOW)

# FAN3226, FAN3227, FAN3228, FAN3229

## TYPICAL PERFORMANCE CHARACTERISTICS

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 12.  $I_{DD}$  (Static) vs. Supply Voltage (Note 13)




Figure 13.  $I_{DD}$  (Static) vs. Supply Voltage (Note 13)




Figure 14.  $I_{DD}$  (Static) vs. Supply Voltage (Note 13)




Figure 15.  $I_{DD}$  (No-Load) vs. Frequency




Figure 16.  $I_{DD}$  (No-Load) vs. Frequency




Figure 17.  $I_{DD}$  (1 nF Load) vs. Frequency

# FAN3226, FAN3227, FAN3228, FAN3229

## TYPICAL PERFORMANCE CHARACTERISTICS (continued)

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 18.  $I_{DD}$  (1 nF Load) vs. Frequency




Figure 19.  $I_{DD}$  (Static) vs. Temperature (Note 13)




Figure 20.  $I_{DD}$  (Static) vs. Temperature (Note 13)




Figure 21.  $I_{DD}$  (Static) vs. Temperature (Note 13)




Figure 22. Input Thresholds vs. Supply Voltage




Figure 23. Input Thresholds vs. Supply Voltage

**TYPICAL PERFORMANCE CHARACTERISTICS** (continued)

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 24. Input Threshold % vs. Supply Voltage




Figure 25. Input Thresholds vs. Temperature




Figure 26. Input Thresholds vs. Temperature




Figure 27. UVLO Thresholds vs. Temperature




Figure 28. UVLO Thresholds vs. Temperature




Figure 29. Propagation Delay vs. Supply Voltage

**TYPICAL PERFORMANCE CHARACTERISTICS** (continued)

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 30. Propagation Delay vs. Supply Voltage




Figure 31. Propagation Delay vs. Supply Voltage




Figure 32. Propagation Delay vs. Supply Voltage




Figure 33. Propagation Delays vs. Temperature




Figure 34. Propagation Delays vs. Temperature




Figure 35. Propagation Delays vs. Temperature

**TYPICAL PERFORMANCE CHARACTERISTICS** (continued)

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 36. Propagation Delays vs. Temperature




Figure 37. Fall Time vs. Supply Voltage




Figure 38. Rise Time vs. Supply Voltage




Figure 39. Rise and Fall Times vs. Temperature




Figure 40. Rise / Fall Waveforms with 1 nF Load




Figure 41. Rise / Fall Waveforms with 10 nF Load

# FAN3226, FAN3227, FAN3228, FAN3229

## TYPICAL PERFORMANCE CHARACTERISTICS (continued)

(Typical characteristics are provided at 25°C and  $V_{DD} = 12\text{ V}$  unless otherwise noted)




Figure 42. Quasi-Static Source Current with  $V_{DD} = 12\text{ V}$




Figure 43. Quasi-Static Sink Current with  $V_{DD} = 12\text{ V}$




Figure 44. Quasi-Static Source Current with  $V_{DD} = 8\text{ V}$




Figure 45. Quasi-Static Sink Current with  $V_{DD} = 8\text{ V}$

13. For any inverting inputs pulled LOW, non-inverting inputs pulled HIGH, or outputs driven HIGH; static  $I_{DD}$  increases by the current flowing through the corresponding pull-up/down resistor, shown in Figure 4.

## TEST CIRCUIT




Figure 46. Quasi-Static  $I_{OUT} / V_{OUT}$  Test Circuit

## APPLICATIONS INFORMATION

**Input Thresholds**

Each member of the FAN322x driver family consists of two identical channels that may be used independently at rated current or connected in parallel to double the individual current capacity. In the FAN3226 and FAN3227, channels A and B can be enabled or disabled independently using ENA or ENB, respectively. The EN pin has TTL thresholds for parts with either CMOS or TTL input thresholds. If ENA and ENB are not connected, an internal pull-up resistor enables the driver channels by default. If the channel A and channel B inputs and outputs are connected in parallel to increase the driver current capacity, ENA and ENB should be connected and driven together.

The FAN322x family offers versions in either TTL or CMOS input thresholds. In the FAN322xT, the input thresholds meet industry-standard TTL-logic thresholds independent of the  $V_{DD}$  voltage, and there is a hysteresis voltage of approximately 0.4 V. These levels permit the inputs to be driven from a range of input logic signal levels for which a voltage over 2 V is considered logic high. The driving signal for the TTL inputs should have fast rising and falling edges with a slew rate of 6 V/ $\mu$ s or faster, so a rise time from 0 to 3.3 V should be 550 ns or less. With reduced slew rate, circuit noise could cause the driver input voltage to exceed the hysteresis voltage and retrigger the driver input, causing erratic operation.

In the FAN322xC, the logic input thresholds are dependent on the  $V_{DD}$  level and, with  $V_{DD}$  of 12 V, the logic rising edge threshold is approximately 55% of  $V_{DD}$  and the input falling edge threshold is approximately 38% of  $V_{DD}$ . The CMOS input configuration offers a hysteresis voltage of approximately 17% of  $V_{DD}$ . The CMOS inputs can be used with relatively slow edges (approaching DC) if good decoupling and bypass techniques are incorporated in the system design to prevent noise from violating the input voltage hysteresis window. This allows setting precise timing intervals by fitting an R-C circuit between the controlling signal and the IN pin of the driver. The slow rising edge at the IN pin of the driver introduces a delay between the controlling signal and the OUT pin of the driver.

**Static Supply Current**

In the  $I_{DD}$  (static) typical performance characteristics (see Figure 12 – Figure 14 and Figure 19 – Figure 21), the curve is produced with all inputs / enables floating (OUT is low) and indicates the lowest static  $I_{DD}$  current for the tested configuration. For other states, additional current flows through the 100 k $\Omega$  resistors on the inputs and outputs shown in the block diagram of each part (see Figure 4 – Figure 7). In these cases, the actual static  $I_{DD}$  current is the value obtained from the curves plus this additional current.

**MillerDrive Gate-Drive Technology**


FAN322x gate drivers incorporate the MillerDrive architecture shown in Figure 47. For the output stage,

a combination of bipolar and MOS devices provide large currents over a wide range of supply voltage and temperature variations. The bipolar devices carry the bulk of the current as OUT swings between 1/3 to 2/3  $V_{DD}$  and the MOS devices pull the output to the high or low rail.

The purpose of the MillerDrive architecture is to speed up switching by providing high current during the Miller plateau region when the gate-drain capacitance of the MOSFET is being charged or discharged as part of the turn-on/turn-off process.

For applications that have zero voltage switching during the MOSFET turn-on or turn-off interval, the driver supplies high peak current for fast switching even though the Miller plateau is not present. This situation often occurs in synchronous rectifier applications because the body diode is generally conducting before the MOSFET is switched on.

The output pin slew rate is determined by  $V_{DD}$  voltage and the load on the output. It is not user adjustable, but a series resistor can be added if a slower rise or fall time at the MOSFET gate is needed.



**Figure 47. Miller Drive Output Architecture**

**Under-Voltage Lockout (UVLO)**

The FAN322x startup logic is optimized to drive ground-referenced N-channel MOSFETs with an under-voltage lockout (UVLO) function to ensure that the IC starts up in an orderly fashion. When  $V_{DD}$  is rising, yet below the 3.9 V operational level, this circuit holds the output low, regardless of the status of the input pins. After the part is active, the supply voltage must drop 0.2 V before the part shuts down. This hysteresis helps prevent chatter when low  $V_{DD}$  supply voltages have noise from the power switching. This configuration is not suitable for driving high-side P-channel MOSFETs because the low output voltage of the driver would turn the P-channel MOSFET on with  $V_{DD}$  below 3.9 V.

### V<sub>DD</sub> Bypass Capacitor Guidelines

To enable this IC to turn a device on quickly, a local high-frequency bypass capacitor  $C_{BYP}$  with low ESR and ESL should be connected between the  $V_{DD}$  and GND pins with minimal trace length. This capacitor is in addition to bulk electrolytic capacitance of 10  $\mu$ F to 47  $\mu$ F commonly found on driver and controller bias circuits.

A typical criterion for choosing the value of  $C_{BYP}$  is to keep the ripple voltage on the  $V_{DD}$  supply to  $\leq 5\%$ . This is often achieved with a value  $\geq 20$  times the equivalent load capacitance  $C_{EQV}$ , defined here as  $Q_{GATE}/V_{DD}$ . Ceramic capacitors of 0.1  $\mu$ F to 1  $\mu$ F or larger are common choices, as are dielectrics, such as X5R and X7R with good temperature characteristics and high pulse current capability.

If circuit noise affects normal operation, the value of  $C_{BYP}$  may be increased to 50–100 times the  $C_{EQV}$ , or  $C_{BYP}$  may be split into two capacitors. One should be a larger value, based on equivalent load capacitance, and the other a smaller value, such as 1–10 nF mounted closest to the  $V_{DD}$  and GND pins to carry the higher frequency components of the current pulses. The bypass capacitor must provide the pulsed current from both of the driver channels and, if the drivers are switching simultaneously, the combined peak current sourced from the  $C_{BYP}$  would be twice as large as when a single channel is switching.

### Layout and Connection Guidelines

The FAN3226–26 family of gate drivers incorporates fast-reacting input circuits, short propagation delays, and powerful output stages capable of delivering current peaks over 2 A to facilitate voltage transition times from under 10 ns to over 150 ns. The following layout and connection guidelines are strongly recommended:

- Keep high-current output and power ground paths separate logic and enable input signals and signal ground paths. This is especially critical when dealing with TTL-level logic thresholds at driver inputs and enable pins.
- Keep the driver as close to the load as possible to minimize the length of high-current traces. This reduces the series inductance to improve high-speed switching, while reducing the loop area that can radiate EMI to the driver inputs and surrounding circuitry.
- If the inputs to a channel are not externally connected, the internal 100 k $\Omega$  resistors indicated on block diagrams command a low output. In noisy environments, it may be necessary to tie inputs of an unused channel to  $V_{DD}$  or GND using short traces to prevent noise from causing spurious output switching.
- Many high-speed power circuits can be susceptible to noise injected from their own output or other external sources, possibly causing output re-triggering. These

effects can be obvious if the circuit is tested in breadboard or non-optimal circuit layouts with long input, enable, or output leads. For best results, make connections to all pins as short and direct as possible.

- The FAN322x is compatible with many other industry-standard drivers. In single input parts with enable pins, there is an internal 100 k $\Omega$  resistor tied to  $V_{DD}$  to enable the driver by default; this should be considered in the PCB layout.
- The turn-on and turn-off current paths should be minimized, as discussed in the following section.

Figure 48 shows the pulsed gate drive current path when the gate driver is supplying gate charge to turn the MOSFET on. The current is supplied from the local bypass capacitor,  $C_{BYP}$ , and flows through the driver to the MOSFET gate and to ground. To reach the high peak currents possible, the resistance and inductance in the path should be minimized. The localized  $C_{BYP}$  acts to contain the high peak current pulses within this driver-MOSFET circuit, preventing them from disturbing the sensitive analog circuitry in the PWM controller.




Figure 48. Current Path for MOSFET Turn-On

Figure 49 shows the current path when the gate driver turns the MOSFET off. Ideally, the driver shunts the current directly to the source of the MOSFET in a small circuit loop. For fast turn-off times, the resistance and inductance in this path should be minimized.




Figure 49. Current Path for MOSFET Turn-Off

### Truth Table of Logic Operation

The FAN3228/FAN3229 truth table indicates the operational states using the dual-input configuration. In a non-inverting driver configuration, the IN<sup>-</sup> pin should be a logic low signal. If the IN<sup>-</sup> pin is connected to logic high, a disable function is realized, and the driver output remains low regardless of the state of the IN<sup>+</sup> pin.

Table 1. TRUTH TABLE OF LOGIC OPERATION

| IN <sup>+</sup> | IN <sup>-</sup> | OUT |
|-----------------|-----------------|-----|
| 0               | 0               | 0   |
| 0               | 1               | 0   |
| 1               | 0               | 1   |
| 1               | 1               | 0   |

In the non-inverting driver configuration in Figure 50, the IN<sup>-</sup> pin is tied to ground and the input signal (PWM) is applied to IN<sup>+</sup> pin. The IN<sup>-</sup> pin can be connected to logic high to disable the driver and the output remains low, regardless of the state of the IN<sup>+</sup> pin.




Figure 50. Dual-Input Driver Enabled, Non-Inverting Configuration

In the inverting driver application in Figure 51, the IN<sup>+</sup> pin is tied high. Pulling the IN<sup>+</sup> pin to GND forces the output low, regardless of the state of the IN<sup>-</sup> pin.




Figure 51. Dual-Input Driver Enabled, Inverting Configuration

### Operational Waveforms

At power-up, the driver output remains low until the V<sub>DD</sub> voltage reaches the turn-on threshold. The magnitude of the OUT pulses rises with V<sub>DD</sub> until steady-state V<sub>DD</sub> is reached. The non-inverting operation illustrated in Figure 52 shows that the output remains low until the UVLO threshold is reached, the output is in-phase with the input.




Figure 52. Non-Inverting Startup Waveforms

For the inverting configuration of Figure 51, startup waveforms are shown in Figure 53. With IN<sup>+</sup> tied to V<sub>DD</sub> and the input signal applied to IN<sup>-</sup>, the OUT pulses are inverted with respect to the input. At power-up, the inverted output remains low until the V<sub>DD</sub> voltage reaches the turn-on threshold, then it follows the input with inverted phase.




Figure 53. Inverting Startup Waveforms

### Thermal Guidelines

Gate drivers used to switch MOSFETs and IGBTs at high frequencies can dissipate significant amounts of power. It is important to determine the driver power dissipation and the resulting junction temperature in the application to ensure that the part is operating within acceptable temperature limits.

The total power dissipation in a gate driver is the sum of two components,  $P_{\text{GATE}}$  and  $P_{\text{DYNAMIC}}$ :

$$P_{\text{TOTAL}} = P_{\text{GATE}} + P_{\text{DYNAMIC}} \quad (\text{eq. 1})$$

**Gate Driving Loss:** The most significant power loss results from supplying gate current (charge per unit time) to switch the load MOSFET on and off at the switching frequency. The power dissipation that results from driving a MOSFET at a specified gate–source voltage,  $V_{\text{GS}}$ , with gate charge,  $Q_{\text{G}}$ , at switching frequency,  $f_{\text{SW}}$ , is determined by:

$$P_{\text{GATE}} = Q_{\text{G}} \cdot V_{\text{GS}} \cdot f_{\text{SW}} \cdot n \quad (\text{eq. 2})$$

$n$  is the number of driver channels in use (1 or 2).

**Dynamic Pre–drive / Shoot–through Current:** A power loss resulting from internal current consumption under dynamic operating conditions, including pin pull–up / pull–down resistors, can be obtained using the “ $I_{\text{DD}}$  (No–Load) vs. Frequency” graphs in Typical Performance Characteristics to determine the current  $I_{\text{DYNAMIC}}$  drawn from  $V_{\text{DD}}$  under actual operating conditions:

$$P_{\text{DYNAMIC}} = I_{\text{DYNAMIC}} \cdot V_{\text{DD}} \cdot n \quad (\text{eq. 3})$$

Once the power dissipated in the driver is determined, the driver junction rise with respect to circuit board can be evaluated using the following thermal equation, assuming  $\psi_{\text{JB}}$  was determined for a similar thermal design (heat sinking and air flow):

$$T_{\text{J}} = P_{\text{TOTAL}} \cdot \psi_{\text{JB}} + T_{\text{B}} \quad (\text{eq. 4})$$

where:

$T_{\text{J}}$  = driver junction temperature;

$\psi_{\text{JB}}$  = (psi) thermal characterization parameter relating temperature rise to total power dissipation; and

$T_{\text{B}}$  = board temperature in location as defined in the [Thermal Characteristics](#) table.

In the forward converter with synchronous rectifier shown in the typical application diagrams, the FDMS8660S is a reasonable MOSFET selection. The gate charge for each SR MOSFET would be 60 nC with  $V_{\text{GS}} = V_{\text{DD}} = 7 \text{ V}$ . At a switching frequency of 500 kHz, the total power dissipation is:

$$P_{\text{GATE}} = 60 \text{ nC} \cdot 7 \text{ V} \cdot 500 \text{ kHz} \cdot 2 = 0.42 \text{ W} \quad (\text{eq. 5})$$

$$P_{\text{DYNAMIC}} = 3 \text{ mA} \cdot 7 \text{ V} \cdot 2 = 0.042 \text{ W} \quad (\text{eq. 6})$$

$$P_{\text{TOTAL}} = 0.46 \text{ W} \quad (\text{eq. 7})$$

The SOIC–8 has a junction–to–board thermal characterization parameter of  $\psi_{\text{JB}} = 43^\circ\text{C/W}$ . In a system application, the localized temperature around the device is a function of the layout and construction of the PCB along with airflow across the surfaces. To ensure reliable operation, the maximum junction temperature of the device must be prevented from exceeding the maximum rating of  $150^\circ\text{C}$ ; with 80% derating,  $T_{\text{J}}$  would be limited to  $120^\circ\text{C}$ . Rearranging Equation 4 determines the board temperature required to maintain the junction temperature below  $120^\circ\text{C}$ :

$$T_{\text{B}} = T_{\text{J}} - P_{\text{TOTAL}} \cdot \psi_{\text{JB}} \quad (\text{eq. 8})$$

$$T_{\text{B}} = 120^\circ\text{C} - 0.46 \text{ W} \cdot 43^\circ\text{C/W} = 100^\circ\text{C} \quad (\text{eq. 9})$$

Consider tradeoffs between reducing overall circuit size with junction temperature reduction for increased reliability.

TYPICAL APPLICATION DIAGRAMS




Figure 54. Forward Converter with Synchronous Rectification




Figure 55. Primary-Side Dual Driver in a Push-Pull Converter




Figure 56. Phase-Shifted Full-Bridge with Two Gate Drive Transformers (Simplified)

# FAN3226, FAN3227, FAN3228, FAN3229

## ORDERING INFORMATION

| Part Number     | Logic                                                                | Input Threshold | Package | Shipping†           |
|-----------------|----------------------------------------------------------------------|-----------------|---------|---------------------|
| FAN3226CMX-F085 | Dual Inverting Channels + Dual Enable                                | CMOS            | SOIC-8  | 2,500 / Tape & Reel |
| FAN3226TMX-F085 |                                                                      | TTL             | SOIC-8  | 2,500 / Tape & Reel |
| FAN3227CMX-F085 | Dual Non-Inverting Channels + Dual Enable                            | CMOS            | SOIC-8  | 2,500 / Tape & Reel |
| FAN3227TMX-F085 |                                                                      | TTL             | SOIC-8  | 2,500 / Tape & Reel |
| FAN3228CMX-F085 | Dual Channels of Two-Input / One-Output Drivers, Pin Configuration 1 | CMOS            | SOIC-8  | 2,500 / Tape & Reel |
| FAN3228TMX-F085 |                                                                      | TTL             | SOIC-8  | 2,500 / Tape & Reel |
| FAN3229CMX-F085 | Dual Channels of Two-Input / One-Output Drivers, Pin Configuration 2 | CMOS            | SOIC-8  | 2,500 / Tape & Reel |
| FAN3229TMX-F085 |                                                                      | TTL             | SOIC-8  | 2,500 / Tape & Reel |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

**Table 2. RELATED PRODUCTS**

| Type       | Part Number | Gate Drive<br>(Note 14)<br>(Sink/Src) | Input<br>Threshold | Logic                                                                            | Package         |
|------------|-------------|---------------------------------------|--------------------|----------------------------------------------------------------------------------|-----------------|
| Dual 2 A   | FAN3216T    | +2.4 A / -1.6 A                       | TTL                | Dual Inverting Channels                                                          | SOIC8           |
| Dual 2 A   | FAN3217T    | +2.4 A / -1.6 A                       | TTL                | Dual Non-Inverting Channels                                                      | SOIC8           |
| Dual 2 A   | FAN3226C    | +2.4 A / -1.6 A                       | CMOS               | Dual Inverting Channels + Dual Enable                                            | SOIC8           |
| Dual 2 A   | FAN3226T    | +2.4 A / -1.6 A                       | TTL                | Dual Inverting Channels + Dual Enable                                            | SOIC8           |
| Dual 2 A   | FAN3227C    | +2.4 A / -1.6 A                       | CMOS               | Dual Non-Inverting Channels + Dual Enable                                        | SOIC8           |
| Dual 2 A   | FAN3227T    | +2.4 A / -1.6 A                       | TTL                | Dual Non-Inverting Channels + Dual Enable                                        | SOIC8           |
| Dual 2 A   | FAN3228C    | +2.4 A / -1.6 A                       | CMOS               | Dual Channels of Two-Input/One-Output,<br>Pin Config.1                           | SOIC8           |
| Dual 2 A   | FAN3228T    | +2.4 A / -1.6 A                       | TTL                | Dual Channels of Two-Input/One-Output,<br>Pin Config.1                           | SOIC8           |
| Dual 2 A   | FAN3229C    | +2.4 A / -1.6 A                       | CMOS               | Dual Channels of Two-Input/One-Output,<br>Pin Config.2                           | SOIC8           |
| Dual 2 A   | FAN3229T    | +2.4 A / -1.6 A                       | TTL                | Dual Channels of Two-Input/One-Output,<br>Pin Config.2                           | SOIC8           |
| Dual 2 A   | FAN3268T    | +2.4 A / -1.6 A                       | TTL                | 20 V Non-Inverting Channel (NMOS) and<br>Inverting Channel (PMOS) + Dual Enables | SOIC8           |
| Dual 4 A   | FAN3213T    | +2.5 A / -1.8 A                       | TTL                | Dual Inverting Channels                                                          | SOIC8           |
| Dual 4 A   | FAN3214T    | +2.5 A / -1.8 A                       | TTL                | Dual Non-Inverting Channels                                                      | SOIC8           |
| Dual 4 A   | FAN3223C    | +4.3 A / -2.8 A                       | CMOS               | Dual Inverting Channels + Dual Enable                                            | SOIC8           |
| Dual 4 A   | FAN3223T    | +4.3 A / -2.8 A                       | TTL                | Dual Inverting Channels + Dual Enable                                            | SOIC8           |
| Dual 4 A   | FAN3224C    | +4.3 A / -2.8 A                       | CMOS               | Dual Non-Inverting Channels + Dual Enable                                        | SOIC8           |
| Dual 4 A   | FAN3224T    | +4.3 A / -2.8 A                       | TTL                | Dual Non-Inverting Channels + Dual Enable                                        | SOIC8, SOIC8-EP |
| Dual 4 A   | FAN3225C    | +4.3 A / -2.8 A                       | CMOS               | Dual Channels of Two-Input/One-Output                                            | SOIC8           |
| Dual 4 A   | FAN3225T    | +4.3 A / -2.8 A                       | TTL                | Dual Channels of Two-Input/One-Output                                            | SOIC8           |
| Single 9 A | FAN3121C    | +9.7 A / -7.1 A                       | CMOS               | Single Inverting Channel + Enable                                                | SOIC8           |
| Single 9 A | FAN3121T    | +9.7 A / -7.1 A                       | TTL                | Single Inverting Channel + Enable                                                | SOIC8           |
| Single 9 A | FAN3122C    | +9.7 A / -7.1 A                       | CMOS               | Single Non-Inverting Channel + Enable                                            | SOIC8           |
| Single 9 A | FAN3122T    | +9.7 A / -7.1 A                       | TTL                | Single Non-Inverting Channel + Enable                                            | SOIC8, SOIC8-EP |

14. Typical currents with OUTx at 6 V and  $V_{DD} = 12$  V.

15. Thresholds proportional to an externally supplied reference voltage.

MillerDrive is trademark of Semiconductor Components Industries, LLC (SCILLC) or its subsidiaries in the United States and/or other countries.

# MECHANICAL CASE OUTLINE


## PACKAGE DIMENSIONS

ON Semiconductor®





**SOIC8**  
CASE 751EB  
ISSUE A



DATE 24 AUG 2017




⌀ 0.25 (M) C B A



0.10



SCALE: 2:1



### NOTES:

- A) THIS PACKAGE CONFORMS TO JEDEC MS-012, VARIATION AA.
- B) ALL DIMENSIONS ARE IN MILLIMETERS.
- C) DIMENSIONS DO NOT INCLUDE MOLD FLASH OR BURRS.
- D) LANDPATTERN STANDARD: SOIC127P600X175-8M

|                  |             |                                                                                                                                                                                  |
|------------------|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| DOCUMENT NUMBER: | 98AON13735G | Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red. |
| DESCRIPTION:     | SOIC8       | PAGE 1 OF 1                                                                                                                                                                      |

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. ON Semiconductor does not convey any license under its patent rights nor the rights of others.

**onsemi**, **Onsemi**, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

### TECHNICAL PUBLICATIONS:

Technical Library: [www.onsemi.com/design/resources/technical-documentation](http://www.onsemi.com/design/resources/technical-documentation)  
onsemi Website: [www.onsemi.com](http://www.onsemi.com)

### ONLINE SUPPORT: [www.onsemi.com/support](http://www.onsemi.com/support)

For additional information, please contact your local Sales Representative at  
[www.onsemi.com/support/sales](http://www.onsemi.com/support/sales)