



DC-DC Switching Regulator and Controller Selector Guide

Step-Down Buck Switching Regulators - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout	Fsw (kHz)	Mode	Enable	Soft-Start	Comments	Temp Range (°C)	Package
	Min	Max									
NCP1500	2.7	5.4	1.0, 1.3, 1.5, 1.8 V	300 mA	270 - 630	Current			PWM or Linear mode. Can be programmed to work in Linear LDO Regulator mode. External Sync.	-40 to 85	Micro8™
NCP1501	2.7	5.2	1.05, 1.35, 1.57, 1.8 V	300 mA	500-1000	Current			Synchronous Rectification. Can be programmed to work in Linear LDO Regulator mode. External Sync.	-40 to 85	Micro8™
NCP1510	2.5	5.2	1.05, 1.35, 1.57, 1.8 V	300 mA	450-1000	Current	✓	✓	Synchronous Rectification. Can be programmed to work in Low Iq (14 uA) Pulsed mode at light loads. External Sync.	-40 to 85	MicroBump-9
NCP1526	2.7	5.5	PWM - 1.2V; LDO - 2.8 V Other options available	PWM: 400 mA LDO: 150 mA	3000	Voltage	✓	✓	Dual output: PWM + LDO. Synchronous Rectification	-40 to 85	Thin DFN-10
NCP1521B	2.7	5.5	0.9 - 3.9 V	600 mA	1500	Current	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5, Thin DFN-6
NCP1522B	2.7	5.5	0.9 - 3.3 V	600 mA	3000	Voltage	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5, Thin DFN-6
NCP1523B	2.7	5.5	0.9 - 3.3 V	600 mA	3000	Voltage	✓	✓	PWM mode. Synchronous Rectification	-40 to 85	MicroBump-8
NCP1530	2.7	5	2.5, 2.7, 3.0, 3.3 V	600 mA	600 - 1200	Current	✓	✓	Automatic PWM/PFM mode. External Synchronization Up to 1.2 MHz	-40 to 85	Micro8™
LM2574	4.5	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	0.5 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
LM2594	4.5	40	Adj (1.23 to 37 V)	0.5 A	150	Voltage	✓	✓	No external compensation	-40 to 125	SOIC-8, PDIP-8
LM2575	4.5	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	1.0 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
LM2595	4.5	40	Adj (1.23 to 37 V)	1.0 A	150	Voltage	✓	✓	No external compensation	-40 to 125	D2PAK, TO-220
NCP1529	2.7	5.5	1.2, 1.8, Adj (0.9-3.3 V)	1.0 A	1700	Current	✓	✓	Auto PWM/PFM mode. Synchronous Rectification	-40 to 85	Thin SOT-23-5
CS51411/3	4.5	40	Down to 1.276 V	1.5 A	260/520	Voltage	✓	✓	Sync capability; Pin-Compatible with LT1375 and LT1376	-40 to 85	SOIC-8, DFN-8
CS51412/4	4.5	40	Down to 1.276 V	1.5 A	260/520	Voltage	✓	✓	External Bias; Pin-Compatible with LT1375 and LT1376	-40 to 85	SOIC-8, DFN-8
NCP1546/7	4.5	40	Down to 1.27 V	1.5 A	170 / 340	Voltage	✓	✓	1 uA Iq; Synchronization	-40 to 125	SOIC-8, DFN-18
NCP1595/A	4.0	5.5	Down to 0.8 V	1.5 A	1200	Current	✓	✓	Internal compensation; Synchronous Rectification	0 to 85	DFN-6
NCP3120/2	4.5	13.2	Down to 0.8 V	2.0/2.0 A	200-2200	Voltage	✓	✓	Auto tracking and sequencing; 180° Out-of-phase operation	-40 to 85	QFN-32
LM2576	4.5	40	3.3, 5, 12, 15, Adj (1.23 to 37 V)	3.0 A	52	Voltage	✓		No external compensation required	-40 to 125	D2PAK, TO-220
LM2596	4.5	40	Adj (1.23 to 37 V)	3.0 A	150	Voltage	✓	✓	No external compensation	-40 to 125	D2PAK, TO-220
MC33166 MC34166	7.5	40	Down to 5.0 V	3.0 A	72	Voltage			Internal thermal shutdown, Cycle-by-Cycle current limit	-40 to 85	D2PAK, TO-220
NCP3121/3	4.5	13.2	Down to 0.8 V	3.0/3.0 A	200-2200	Voltage	✓	✓	Auto tracking and sequencing; 180° Out-of-phase operation	-40 to 85	QFN-32
MC33167 MC34167	7.0	40	Down to 5.0 V	5.0 A	72	Voltage			Standby Mode < 36 uA	-40 to 85	D2PAK, TO-220
NCP3101	4.5	13.2	Down to 0.8 V	6.0 A	275	Voltage	✓	✓	Highly integrated 6 A output	-40 to 85	QFN-40
NCP3102	4.5	13.2	Down to 0.8 V	10.0 A	275	Voltage	✓	✓	Highly integrated 10 A output	-40 to 85	QFN-40

Step-Up Boost Switching Regulators - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout	Fsw (kHz)	Mode	Enable	Soft-Start	Comments	Temp Range (°C)	Package
	Min	Max									
NCP1403	1.2	5.5	Up to 15 V	50 mA	300	Current	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1406	1.4	5.5	Up to 25 V	50 mA	1000	Current	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1400	0.8	5.5	1.9 - 5.0 V	100 mA	180	Voltage	✓	✓	PWM mode	-40 to 85	SOT-23-5
NCP1402	0.8	5.5	1.8 - 5.0 V	200 mA	180	Voltage	✓	✓	PFM mode	-40 to 85	SOT-23-5
NCP1410	1.0	5.5	Vin to 5.5 V	250 mA	600	Current	✓		PFM mode. Synchronous Rectification, Low-battery detect	-40 to 85	Micro8™
NCP1423	0.8	Vout	1.8 - 5.5 V	400 mA	600	Current	✓	✓	PFM mode. Synchronous Rectification, True-cutoff, Low-battery detect	-40 to 85	Micro-10
NCP1421	1.0	5.0	1.5 - 5.0 V	600 mA	1200	Current	✓	✓	PFM Sync-rect, True-cutoff, Low-battery detect	-40 to 85	Micro8
NCP1422	1.0	5.0	1.5 - 5.0 V	800 mA	1200	Current	✓	✓	PFM mode. Synchronous Rectification, True-cutoff, Low-battery detect	-40 to 85	DFN-10
NCP5030	2.7	5.5	2.2 - 5.5 V	1.2 A	1000	Current	✓	✓	Buck/ Boost Converter - can supply either regulated current or regulated output voltage	-40 to 85	DFN-12
CS5171	2.7	30	1.276 to 40 V	1.5 A	280	Current		✓	LT1372/1373 Compatible	-40 to 85	SOIC-8
CS5172	2.7	30	-2.5 to 40 V	1.5 A	280	Current		✓	Flyback & SEPIC	-40 to 85	SOIC-8
CS5173	2.7	30	1.276 to 40 V	1.5 A	560	Current		✓	Easy External Synchronization	-40 to 85	SOIC-8
CS5174	2.7	30	-2.5 to 40 V	1.5 A	560	Current		✓	Negative feedback polarity	-40 to 85	SOIC-8

Multi-Topology (Step-Up, Step-Down, Inverting) Switching Regulators - Internal Switch

Device	Vin (V)		Vout Options (Adj Range)	Iout (A)	Fsw (kHz)	Enable	Mode	Step Up	Step Down	Step Up/Down	Inv	Comments	Temp Range (°C)	Package
	Min	Max												
MC33063 MC34063	3.0	40	Down to 2.5 V	1.5	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Minimal number of external components	-40 to 85	SOIC-8, PDIP-8
NCP3063	3.0	40	Down to 2.5 V	1.5	Up to 250	✓	Hysteretic	✓	✓	✓	✓	Higher Fsw for optimized size & efficiency	-40 to 85	PDIP-8, SOIC-8, DFN-8
NCP3064	3.0	40	Down to 2.5 V	1.5	150	✓	Hysteretic	✓	✓	✓		Enable; Standby Mode < 100 µA	0 to 70	PDIP-8, SOIC-8, DFN-8
NCP3065	3.0	40	Down to 0.2 V	1.5	Up to 250	✓	Hysteretic	✓	✓	✓	✓	Driver for HB-LED/constant current source	-40 to 85	DFN-8, SOIC-8, PDIP-8
NCP3066	3.0	40	Down to 0.2 V	1.5	150	✓	Hysteretic	✓	✓	✓		Driver for HB-LED; Dedicated Enable pin for PWM dimming	0 to 70	PDIP-8, SOIC-8, DFN-8
CS5171	2.7	30	1.276 to 40 V	1.5	280		Current	✓			✓	LT1372/1373 Compatible	-40 to 85	SOIC-8
CS5172	2.7	30	-2.5 to 40 V	1.5	280		Current	✓			✓	Flyback & SEPIC	-40 to 85	SOIC-8
CS5173	2.7	30	1.276 to 40 V	1.5	560		Current	✓			✓	Easy External Synchronization	-40 to 85	SOIC-8
CS5174	2.7	30	-2.5 to 40 V	1.5	560		Current	✓			✓	Negative feedback polarity	-40 to 85	SOIC-8
MC33166 MC34166	7.5	40	Down to 5.0 V	3.0	72		Voltage		✓	✓	✓	Internal thermal shutdown, Cycle-by-Cycle current limit	-40 to 85	D2PAK, TO-220
MC33163 MC34163	2.5	40	Down to 1.25 V	3.4	Up to 100	✓	Hysteretic	✓	✓	✓	✓	Minimal number of external components	-40 to 85	SOIC-16W, PDIP-16
NCP3163	2.5	40	Down to 1.25 V	3.4	Up to 300	✓	Hysteretic	✓	✓	✓	✓	Higher Fsw for optimized size & efficiency	-40 to 85	SOIC-16WEP
MC33167 MC34167	7.0	40	Down to 5.0 V	5.0	72		Voltage		✓	✓	✓	Standby Mode < 36 µA	-40 to 85	D2PAK, TO-220

Switching Controllers for Step-Down Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft-Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
CS51033	3.3	5.0	Down to 1.25 V	2%	200 - 700	Hysteretic		✓		No compensation required; PFET	-40 to 85	SOIC-8
NCP1550	2.5	5.5	1.8 - 3.3 V (factory prefixed)	2.0%	600	Voltage	✓	✓		Auto PWM/ PFM mode; 2 A drive capability	-40 to 85	SOT-23-5
NCP1571	2.0	12	Down to 0.980 V	1.0%	200	Voltage	✓	✓	✓	12 V bias supply	0 to 125	SOIC-8
NCP1575	2.0	12	Down to 0.980 V	1.0%	200 - 500	Voltage		✓	✓	12 V bias supply	0 to 125	SOIC-8
NCP1579	4.5	13.2	Down to 0.8 V	2.0%	275	Voltage	✓	✓		1 A drive capability; Short circuit protection	0 to 70	SOIC-8
NCP1587/A	4.5	13.2	Down to 0.8 V	1.0%	200 / 275	Voltage	✓	✓		1 A drive capability; Short circuit protection	0 to 70	SOIC-8
CS51031	4.5	16	Down to 1.25 V	2%	200 - 700	Hysteretic		✓		No compensation required; PFET	-40 to 85	SOIC-8
IR3638	7.0	20	Down to 0.8 V	1.0%	400	Voltage	✓	✓		Power sequencing / tracking	0 to 125	SOIC-14
NCP5212	4.7	27	Down to 0.8 V	0.8%	300	Current	✓	✓	✓	Light load efficiency; AVP; TRE	-40 to 85	QFN-16
SG3525	8.0	35	Down to 5.1 V	1%	100 - 400	Voltage	✓	✓		Flexible configurations; ST Compatible	0 to 70	SOIC-16W, PDIP-16
NCV8851	4.5	40	Down to 0.8 V	2.0%	175 - 500	Current	✓	✓	✓	Meets automotive load dump requirements	-40 to 150	TSSOP-20
NCP1034	8.0	100	Down to 1.25 V	1.5%	Up to 500	Voltage	✓	✓	✓	2 A drive capability; Synchronization	-40 to 125	SOIC-16

Dual Switching Controllers for Step-Down Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft-Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
NCP5422	10.8	13.2	Down to 1.0 V	2.0%	150 - 600	Voltage	✓	✓	✓	Hiccup mode overcurrent protection	0 to 70	SOIC-16
NCP5424	10.8	13.2	Down to 1.0 V	2.0%	150 - 600	Voltage	✓	✓	✓	Hiccup & cycle-by-cycle overcurrent	0 to 70	SOIC-16
NCP5425	4.6	13.2	Down to 0.8 V	1.0%	150 - 750	Voltage	✓	✓	✓	1.5A peak drive capability	0 to 125	TSSOP-20
TL494	7.0	40	0.3 V Ext Adj	5.0%	Up to 200	Voltage				Buck, boost, forward, flyback	-40 to 125	SOIC-16, PDIP-16
TL594	7.0	40	0.3 V Ext Adj	1.5%	Up to 300	Voltage				Buck, boost, forward, flyback	-40 to 85	SOIC-16, PDIP-16, TSSOP-16

Switching Controllers for Step-Up Non-Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft-Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
NCP1450	0.9	5.5	1.9 - 5.0 V (factory prefixed)	2.5%	180	Voltage	✓	✓		PWM mode	-40 to 85	SOT-23-5

Switching Controllers for Step-Down Isolated Topologies

Device	Vin (V)		Vout Options (Adj Range)	Vout Accuracy	Fsw (kHz)	Mode	Enable	Soft-Start	Sync	Comments	Temp Range (°C)	Package
	Min	Max										
CS51221	3.3	72	Down to 1.26 V	2%	Up to 1000	Voltage		✓		Programmable features; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
CS51021	3.3	72	Down to 5.0 V	1%	200 - 1000	Current		✓		Synch; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
CS51022	3.3	72	Down to 5.0 V	1%	200 - 1000	Current		✓		Sleep mode; Bias for startup	-40 to 85	SOIC-16, TSSOP-16
CS5124	7.7	75	External	-	400	Current	✓	✓		Small PCB footprint; Bias for startup	-40 to 105	SOIC-8
NCP1030	10	200	2.5 Up to Vin	2%	Up to 1000	Voltage	✓	✓		PoE applications; Integrated Switch	-40 to 125	Micro8™
NCP1031	10	200	2.5 Up to Vin	2%	Up to 1000	Voltage	✓	✓		PoE applications; Integrated Switch	-40 to 125	SOIC-8

Sales and Design Assistance from ON Semiconductor

ON Semiconductor Distribution Partners		
AMSC Co.	www.amsco.jp	(81) 422 54 6622
Arrow Electronics	www.arrow.com	(800) 777-2776
Avnet	www.em.avnet.com	(800) 332-8638
Digi-Key	www.digikey.com	(800) 344-4539
EBV Elektronik	www.ebv.com/en/locations.html	(49) 8121 774-0
Fuji Electric Co.	www.fujiele.co.jp	(81) 3 3814 1411
Future & FAI Electronics	www.futureelectronics.com/contact	1-800-FUTURE1 (388-8731)
KH Electronics Inc.	www.khelec.com/kor	(82) 42 471 8521
Marubun	www.marubun.co.jp	(81) 3 3639 5630
Mitsui Electronics Inc.	www.btel.co.jp	(81) 3 6403 5900
Mouser Electronics	www.mouser.com	(800) 346-6873
Newark/ Farnell	www.farnell.com/onsemi	(800) 4-NEWARK
NU Horizons	www.nuhorizons.com	(800) 275-8488
Promate Electronic Co.	www.promate.com.tw	(886) 2 2659 0303
Segyung Bristestone Co.	www.bristestone.com	(82) 2 3218 1511
Serial Microelectronics, HK	www.serialsys.com.hk	(852) 2790 8220
Taewon Inc.	www.taewon.net	(82) 2 6679 9000
Tokyo Electron Device Co.	www.teldevice.co.jp	(81) 45 443 4000
World Peace Industries Co.	www.wpi-group.com	(852) 2365 4860
WT Microelectronics Co.	www.wtmecc.com	(852) 2950 0820
Yosun Electronics	www.yosun.com.tw	(886) 2 2659 8168

For a comprehensive listing of
ON Semiconductor Sales Offices, please visit:
www.onsemi.com/salesupport

INTERNATIONAL		
GREATER CHINA	Beijing	86-10-8518-2323
	Chengdu	86-28-8678-4078
	Hong Kong	852-2689-0088
	Shenzhen	86-755-8209-1128
	Shanghai	86-21-5131-7168
	Taipei, Taiwan	886-2-2377-9911
FRANCE	Paris	33 (0)1 39-26-41-00
GERMANY	Munich	49 (0) 89-93-0808-0
ISRAEL	Raanana	972 (0) 9-9609-111
ITALY	Milan	39 02 9239311
JAPAN	Tokyo	81-3-5773-3850
KOREA	Seoul	82-2-2190-3500
MALAYSIA	Penang	60-4-226-9368
SINGAPORE	Singapore	65-6391-1260
SLOVAKIA	Piestany	421 33 790 2450
UNITED KINGDOM	Slough	44 (0) 1753 70 1676

AMERICAS REP FIRMS			
Alabama	Huntsville	e-Components	(256) 533-2444
Arizona	Tempe	Centaur	(480) 839-2320
Brazil	Countrywide	Ammon & Rizos	(+55) 11-4688-1960
California	Bay Area	L2	(408) 433-9388
	Calabasas	Centaur	(818) 878-5800
	Irvine	Centaur	(949) 261-2123
	San Diego	Centaur	(858) 278-4950
	Simi Valley	Centaur	(805) 579-0519
Canada	Eastern Canada	Astec	(905) 607-1444
	Western Canada	Sifore	(503) 977-6267
Connecticut	Statewide	Genesis Associates	(781) 270-9540
Delaware	Statewide	S.J. Mid-Atlantic	(856) 866-1234
Florida	Statewide	e-Components	(888) 468-2444
Georgia	Atlanta	e-Components	(888) 468-2444
Idaho	Eagle	First Source of Idaho, Inc.	(800) 282-9855
Illinois	St. Charles (South)	Stan Clothier Company	(847) 781-4010
	Palatine (North)	HLC Ltd.	(847) 358-6500
Indiana	Fishers	Bear VAI	(317) 570-0707
Iowa	Cedar Rapids	Essig & Associates	(319) 363-8703
Kansas	Overland Park	Stan Clothier Company	(913) 894-1675
Maryland	Columbia	Third Wave Solutions	(410) 290-5990
Massachusetts	Burlington	Genesis Associates	(781) 270-9540
Mexico	Countrywide	Phoenix Rep	(+52) 33-3123-9198
Michigan	St. Joseph	Bear VAI	(440) 526-1991
Minnesota	Eden Prairie	Stan Clothier Company	(952) 944-3456
Missouri	St. Charles	Stan Clothier Company	(636) 916-3777
New Jersey	Mount Laurel	S.J. Mid-Atlantic	(856) 866-1234
	Statewide	S.J. Metro	(516) 942-3232
New York	Binghamton	TriTech - Full Line Rep	(607) 722-3580
	Jericho	S.J. Metro	(516) 942-3232
	Rochester	TriTech - Full Line Rep	(585) 385-6500
	Statewide	S.J. Mid-Atlantic	(856) 866-1234
North Carolina	Raleigh	e-Components	(888) 468-2444
Ohio	Brecksville	Bear VAI Technology	(440) 526-1991
Oregon	Portland	SiFore Technical	(503) 977-6267
Pennsylvania	Statewide	S.J. Mid-Atlantic	(856) 866-1234
Puerto Rico	Countrywide	e-Components	(888) 468-2444
Texas	Austin	West Associates	(512) 343-1199
	Houston	West Associates	(832) 717-3774
	Richardson	West Associates	(972) 680-2800
Washington	Bellevue	SiFore Technical	(425) 990-4701
Wisconsin	Eden Prairie (NW)	Stan Clothier Company	(608) 882-0686
	Milwaukee (SE)	HLC Ltd.	(847) 358-6500

Apr-09

ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada.
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local
Sales Representative