

# ONC18: G/MS

---

*Process Technology*

## **ONC18: 0.18 $\mu\text{m}$ CMOS Process Technology - G/MS**



**ON Semiconductor®**

[www.onsemi.com](http://www.onsemi.com)

---

### **Overview**

The ONC18 process from ON Semiconductor is an industry compatible 0.18  $\mu\text{m}$  CMOS technology manufactured in the United States. This full featured process includes 1.8 V/3.3 V dual gate I/Os, nominal and high value MIM capacitors, resistors, and six levels of metal. A comprehensive design kit offers an expansive core, I/O,

and memory library. Specialty services including stitching, planarized passivation, and shuttle prototyping are available. ONC18 also serves as a platform for highly integrated high voltage mixed-signal processes ideal for many automotive, industrial, medical, and defense applications.

### **Features**

- 4 to 6 Metal Layers
- 1.0 fF/ $\mu\text{m}^2$  Metal-insulator-metal (MIM) Capacitor
- 2.0 fF/ $\mu\text{m}^2$  Metal-insulator-metal (MIM) Capacitors (Design Dependent)
- 4.0 fF/ $\mu\text{m}^2$  Metal-insulator-metal (MIM) Stacked Capacitors (Design Dependent)
- Salicide Process with Optional Blocking
- 1.8 V, 3.3 V Core Voltage and 3.3 V I/O Voltage with 5 V Tolerant Input
- Poly, Diffusion, and Well Resistors
- Bipolar Transistors: LV Parasitic
- Die Stitching
- SEU/SEL Libraries Available
- Specialty Devices
  - ◆ 5 V Zener Diodes
  - ◆ Schottky Diodes
  - ◆ Deep N-Well (Triple Well/ Noise Isolation)

# ONC18: G/MS

## PROCESS CHARACTERISTICS

Operating Voltage	1.8 V, 3.3 V
Substrate Material	P-Type
Drawn Transistor Length	0.18 $\mu\text{m}$
Gate Oxide Thickness	2.9 nm/6.5 nm
Contact/Via Size	0.22 $\mu\text{m}$ /0.26 $\mu\text{m}$
Metal Thickness	M1-MTop-1 – 0.56 $\mu\text{m}$ MT(0.8 $\mu\text{m}$ ) – 0.94 $\mu\text{m}$ MT(3.0 $\mu\text{m}$ ) – 3.14 $\mu\text{m}$

## CONTACTED METAL PITCH

Metal 1	0.46 $\mu\text{m}$
Metal 2-Top-1	0.56 $\mu\text{m}$
Metal Top (0.8 $\mu\text{m}$ )	0.9 $\mu\text{m}$
Metal Top (3.0 $\mu\text{m}$ )	6 $\mu\text{m}$
Metal Composition	Al-0.5%Cu/TiN

Content	ONC18 G/MS	I4T 45 V/70 V	ONC18 5 V/30 V	ONC18 18 V/18 V	Added Masks from Base	Notes
<b>TEMPERATURE RANGE</b>						
Minimum	-40°C	-40°C	-40°C	-40°C		
Maximum	135°C	200°C	135°C	135°C		

## CMOS (Isat [ $\mu\text{A}/\mu$ width] shown)

1.8V NMOS – Generic Threshold	600	600	600	600	N	
1.8V PMOS – Generic Threshold	-260	-260	-260	-260	N	
1.8V Native NMOS	365	365	365	365	N	
1.8V Low Vt NMOS	350	350	350	350	1	
1.8V NMOS – High Threshold ~ 0.65 V	410	410	410	410	2	
1.8V PMOS – High Threshold ~ -0.65 V	-175	-175	-175	-175	2	
3.3V NMOS – Generic Threshold	550	550	NA	NA	N	
3.3V PMOS – Generic Threshold	-285	-285	NA	NA	N	
3.3V Native NMOS	540	540	NA	NA	N	
3.3V Low Vt NMOS	370	370	NA	NA	1	
5.0V NMOS – Generic Threshold (SVt)	NA	NA	570	570	N	
5.0V PMOS – Generic Threshold (SVt)	NA	NA	-258	-258	N	
5.0V NMOS – Medium Threshold (XVt)	NA	NA	420	420	1	
5.0V PMOS – Medium Threshold (XVt)	NA	NA	-158	-158	1	
5.0V NMOS – Low Threshold (LVt)	NA	NA	390	390	1	
5.0V PMOS – Low Threshold (LVt)	NA	NA	-124	-124	1	
5.0V Native NMOS	NA	NA	14	14	N	

## CAPACITORS (BV [V] shown)

MiM Capacitor – 1 fF/ $\mu\text{m}^2$	>20 V	>20 V	>20 V	>20 V	1	
High Capacitance MIM – 2 fF/ $\mu\text{m}^2$	>10 V	>10 V	>10 V	>10 V	1	
Stacked MiM Capacitor – 4 fF/ $\mu\text{m}^2$	>10 V	>10 V	>10 V	>10 V	2	
Linear MOSCAP (Thick) – ~4 fF/ $\mu\text{m}^2$	>5 V	>5V	NA	NA	1	

## ONC18: G/MS

Content	ONC18 G/MS	I4T 45 V/70 V	ONC18 5 V/30 V	ONC18 18 V/18 V	Added Masks from Base	Notes
---------	---------------	------------------	-------------------	--------------------	--------------------------------	-------

### CAPACITORS (BV [V] shown)

Linear MOSCAP (Thin) – ~8 fF/μm <sup>2</sup>	>2.5 V	>2.5V	>2.5 V	>2.5V	1	
Metal Finger Capacitor – 0.5 & 0.7 fF/μm <sup>2</sup>	>20 V	>20 V	>20 V	>20 V	N	
HV Metal Finger Cap – 0.23 fF/μm <sup>2</sup> (>0.45 μm Space)	>100 V	>100V	>100V	>100V	N	>0.45 μm Spacing required.

### RESISTORS (Rsheet [Ω/sq] shown)

N+ w/ Salicide	7	7	7	7	N	
N+ w/o Salicide	60	60	60	60	N	
P+ w/ Salicide	7	7	7	7	N	
P+ w/o Salicide	127	127	127	127	N	
N+ Poly w/ Salicide	7	7	7	7	N	
N+ Poly w/o Salicide	290	290	290	290	N	
P+ Poly w/ Salicide	7	7	7	7	N	
P+ Poly w/o Salicide	311	311	311	311	N	
N-Well under STI	910	910	910	910	N	
"Low" TC Resistor	295	295	295	295	1	
High Value Resistor	1035	1035	1035	1035	1	

### HIGH VOLTAGE (Rsp [mΩ\*mm<sup>2</sup>] shown)

Deep Trench Isolation (DTI)		✓				
3.3V Gate / 15V Drain Analog NLD MOS	41	NA	NA	NA	N	
3.3V Gate / 15V Drain NLD MOS Switch	8.5	NA	NA	NA	N	
3.3V Gate / 15V Drain PLD MOS	34.5	NA	NA	NA	N	
5.0V Gate / 18V Drain NLD MOS	NA	NA	17	17	4	5 V 30 V Flow
5.0V Gate / 18V Drain PLD MOS	NA	NA	45	45	4	5 V 30 V Flow
5.0V Gate / 24V Drain NLD MOS	NA	NA	21.5	21.5	4	5 V 30 V Flow
5.0V Gate / 24V Drain PLD MOS	NA	NA	60	60	4	5 V 30 V Flow
5.0V Gate / 30V Drain NLD MOS	NA	NA	24.5	24.5	4	5 V 30 V Flow
5.0V Gate / 30V Drain PLD MOS	NA	NA	68	68	4	5 V 30 V Flow
18V Gate / 18V Drain Symetrical isolat- ed NLD MOS	NA	NA	NA	58	11	18 V 18 V Flow
18V Gate / 18V Drain Symetrical,isolat- ed, analog NLD MOS	NA	NA	NA	60	11	18 V 18 V Flow
18V Gate / 18V Drain Asymetrical, iso- lated NLD MOS	NA	NA	NA	23	11	18 V 18 V Flow
18V Gate / 18V Drain Asymetrical PLD- MOS	NA	NA	NA	49.5	11	18 V 18 V Flow
18V Gate / 18V Drain Symetrical PLD- MOS	NA	NA	NA	87	11	18 V 18 V Flow
18V Gate / 18V Drain Symetrical, analog PLD MOS	NA	NA	NA	180	11	18 V 18 V Flow
3.3V Gate / 30V Drain NLD MOS Switch / Analog	NA	32 / 48.5	NA	NA	7	45 V or 70 V Flow

## ONC18: G/MS

Content	ONC18 G/MS	I4T 45 V/70 V	ONC18 5 V/30 V	ONC18 18 V/18 V	Added Masks from Base	Notes
---------	---------------	------------------	-------------------	--------------------	--------------------------------	-------

### HIGH VOLTAGE (Rsp [ $m\Omega \cdot mm^2$ ] shown)

3.3V Gate / 30V Drain PLDMOS Switch / Analog	NA	75 / 112	NA	NA	7	45 V or 70 V Flow
3.3V Gate / 45V Drain NLD MOS Switch / Analog	NA	49 / 78	NA	NA	7	45 V or 70 V Flow
3.3V Gate / 45V Drain PLDMOS Switch / Analog	NA	132 / 183	NA	NA	7	45 V or 70 V Flow
3.3V Gate / 70V Drain NLD MOS Switch / Analog	NA	97 / 173	NA	NA	9	70 V Flow
3.3V Gate / 70V Drain PLDMOS Switch / Analog	NA	231 / 280	NA	NA	9	70 V Flow

### BIPOLAR TRANSISTORS

LV Parasitic Bipolars	✓	✓	✓	✓	N	
HV Parasitic Bipolars		✓	✓	✓	N	

### NON-VOLATILE MEMORY

CMOS LogicEE Trim	✓	✓			N	
High Temperature CMOS LogicEE Trim		R&D			N	
Poly Fuse OTP		✓	✓	✓	N	
LogicEE MTP			R&D	R&D	N	
OTP (Sidense Oxide Rupture OTP)	✓	✓			N	

### SPECIALTY DEVICES

5V Zener Diode	✓	✓	✓	✓	1	
5.5V Zener Diode			✓	✓	1	
Free Zener Diode (5.5 to 6.5V)			✓	✓	N	
Schottky Diode	✓	✓	✓	✓	1	
HV Schottky Diode		✓	✓	✓	N	
Deep N-well (Triple Well / Noise Isolation)	✓	✓	✓	✓	1	

### LIBRARIES

(All values typical at 1.8 V, 25°C)

Front-End Digital Design
Digital
Synthesis Libraries
Simulation Libraries
Analog
Design Rules
Spice Models

## ONC18: G/MS

Standard Core Cell	Density (gates/ mm <sup>2</sup> )	Operating Voltage	Leakage (nW)	Propagation Delay (ps)	Dynamic Power (mW/MHz/gate)
1.8 V Standard Core Cell	99.6k	1 V, 1.5 V, 1.8 V	0.136	137 with 0.015 pF L	0.000031
1.8 V Low Leakage Core Cell	99.6k	1.5 V, 1.8 V	0.008	171 with 0.0148 pF L	0.000021
3.3 V High Voltage Core Cell	70.8k	3.3 V	0.00097	112 with 0.0194 pF L	0.00016
Level Shifter	n/a	1.8 V, 3.3 V	n/a	n/a	n/a

\*All the data derived from 2nd cell under nominal voltage and 25°C .

## ONC18: G/MS

IO Library Description	CUP Support	DTI Support	N-well Option	5 V Process Support	Operating Voltage (±10%)	5 V Tolerant	3 V Tolerant	~ Pad Height (µm)	~ Inline / (Staggered) Pad Pitch (µm)	Max Output Strength per Pad (mA)	Top Metal Option	
1.8 V	Yes	Yes	Regular	Y	1.0 V, 1.8 V	N	Y	117	84	12	4, 5, 6	
3.3 V w/level-shift				N	2.5 V, 3.3 V	Y	N	130/146	84/96	12	4, 5, 6	
3.3 V				N	1.8 V, 3.3 V	Y	N	121/135	84/96	12	4, 5, 6	
1.8 V		No	No	Deep	Y	1.0 V, 1.8 V	N	Y	136	84	12	4, 5, 6
3.3 V w/level-shift					N	3.3 V	Y	N	152	84	12	4, 5, 6
3.3 V					N	1.8 V, 3.3 V	Y	N	132	84	12	4, 5, 6
5.0 V					Y	1.8 V, 2.5 V, 3.3 V, 5.0 V	Y	N	132	84	12	4, 5, 6
3.3 V	N				1.8 V, 3.3 V	Y	N	221	84	12	4, 5, 6	
1.8 V	Y				1.0 V, 1.8 V	N	Y	226	84	12	4, 5, 6	
5.0 V	Y				1.8 V, 2.5 V, 3.3 V, 5.0 V	Y	N	222	84	12	4, 5, 6	
3.3 V w/level-shift	No	Yes	Regular	N	2.5 V, 3.3 V	Y	N	220	84	12	4, 5, 6	
1.8 V pad limited				Y	1.8 V	N	N	235	60 / (40)	24	5, 6	
2.5 V pad limited w/1.8V level-shift				N	2.5 V	N	Y	235	60 / (40)	16	5, 6	
3.3 V pad limited w/1.8V level-shift				N	3.3 V	Y	N	235	60 / (40)	24	5, 6	
3.3 V pad limited w/o level-shift				N	3.3 V	Y	N	235	60 / (40)	16	5, 6	

### MEMORY OPTIONS

Compiled Memory Description	MEM-Type	Max Capacity per Instance	Bit Density (eq. bits/mm <sup>2</sup> ) (Note 1)	Operating Voltage (V)	Max Frequency (MHz) (Note 2)	Leakage Current (µA) (Note 2)	Dynamic Power (nW/MHz) (Note 2)
ONC18 HVT Single port SRAM	SRAM	589 kbits	160k	1.0, 1.5 V, 1.8 V	200	2	311
ONC18 HVT Dual port SRAM	DPRAM	294 kbits	80k	1.0, 1.5 V, 1.8 V	200	3	285
ONC18 HVT ROM	ROM	1.1 kbits	900k	1.0, 1.5 V, 1.8 V	150	0.5	183
ONC18 SVT Single port SRAM	SRAM	589 kbits	160k	1.0, 1.2 V 1.5 V, 1.8 V	300	50	310
ONC18 SVT Dual port SRAM	DPRAM	294 kbits	80k	1.0, 1.2 V 1.5 V, 1.8 V	300	70	300
ONC18 SVT ROM	ROM	1.1 Mbits	900k	1.0, 1.2 V 1.5 V, 1.8 V	200	40	141
ONC18 3.3 V Signal port SRAM (Note 3)	SRAM	589 kbits	110k	1.8 V, 3.3 V	100	0.5	n/a
ONC18 3.3 V Dual port SRAM (Note 3)	DPRAM	589 kbits	75k	1.8 V, 3.3 V	100	0.5	n/a
ONC18 3.3 V ROM (Note 3)	ROM	589 kbits	850k	1.8 V, 3.3 V	100	0.1	n/a

1. All the data derived from 256 kb instance.
2. Max frequency and leakage current evaluated based on 256 kbit configuration (4kx64), at PwcsV162T125.
3. This Memory Compiler is under development .

# ONC18: G/MS

## NON-VOLATILE MEMORY

### OTP – One Time Programmable (Sidense Oxide Rupture OTP)

1k-bit array and 256 kbit array
In field programming capable

## CAD TOOL COMPATIBILITY

Digital Design	Cadence Design Kit	Mentor Design Kit	Other
Digital Symbols	Virtuoso	Pyxis Schematic and Language Editor Interface	
RTL Synthesis	Cadence RTL	Mentor Leonardo	Synopsys Design Compiler Explorer
Scan Insertion		Mentor DFT advisor	Synopsys Design DFT compiler
Static and Timing Analysis			Synopsys Primitime
Power Analysis			Synopsys Primepower
Digital Simulation	Cadence Incisive	Mentor Questa	
Formal Verification	Cadence Conformal	Mentor Formal Pro	Synopsys Formality
P&R	Encounter	Olympus-SOC	Synopsys IC compiler
Test ATE	Cadence Encounter Test	Tessent	Synopsys Tetramax

## ANALOG/MIXED-SIGNAL DESIGN

Schematic View and Sizing	Virtuoso	Pyxis Schematic Editor	
	ADE L-XL-GXL	Pyxis Simulation	
Analog Simulation	Spectre-AP-UltraSim	IC Analyst	HSPICE
		Eldo-Eldo Premier-Adit	
Analog Layout	Virtuoso-XL	Pyxis DLA	
Routing	VSR (CCAR, VCR)	iroute-Pyxis Custom Router	


## TOP-LEVEL

Symbol Editor	Virtuoso	Pyxis Schematic and Language Editor Interface	
Top-level Simulation	Cadence AMS	Mentor Questa - ASMS	
Top-level Router		Pyxis Custom Router	

## VERIFICATION

DRC		Calibre	
LVS		Calibre	
Robustness		Calibre PERC	
Analog Parasitic Extraction		Calibre xRC-PEX	
Digital Parasitic Extraction			Synopsys StarRC

# ONC18: G/MS

ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## PUBLICATION ORDERING INFORMATION

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor  
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA  
**Phone:** 303-675-2175 or 800-344-3860 Toll Free USA/Canada  
**Fax:** 303-675-2176 or 800-344-3867 Toll Free USA/Canada  
**Email:** [orderlit@onsemi.com](mailto:orderlit@onsemi.com)

**N. American Technical Support:** 800-282-9855 Toll Free  
USA/Canada  
**Europe, Middle East and Africa Technical Support:**  
Phone: 421 33 790 2910  
**Japan Customer Focus Center**  
Phone: 81-3-5817-1050

**ON Semiconductor Website:** [www.onsemi.com](http://www.onsemi.com)  
**Order Literature:** <http://www.onsemi.com/orderlit>  
For additional information, please contact your local  
Sales Representative