



Is Now Part of



**ON Semiconductor®**

To learn more about ON Semiconductor, please visit our website at

[www.onsemi.com](http://www.onsemi.com)

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

**User Guide for**  
**FEBFOD8316 Evaluation Board**

**2.5 A Output Current, IGBT Drive**  
**Optocoupler with Desaturation Detection**  
**and Isolated Fault Sensing**

**Featured Fairchild Product/s:**  
**FOD8316**

*Direct questions or comments  
about this evaluation board to:  
“Worldwide Direct Support”*

[Fairchild Semiconductor.com](http://Fairchild Semiconductor.com)

## Table of Contents

|   |    |
|---|----|
| 1. Overview .....                       | 3  |
| 1.1. Features and Benefits .....        | 3  |
| 1.2. Applications .....                 | 4  |
| 2. Operations .....                     | 5  |
| 3. Circuit Schematic .....              | 7  |
| 4. Setup and Operation .....            | 9  |
| 5. Test Procedures and Conditions ..... | 9  |
| 6. Scope Shots .....                    | 11 |
| 7. Conclusion .....                     | 13 |
| 8. Revision History .....               | 14 |

## 1. Overview

Fairchild Semiconductor's FOD8316 smart gate driver optocoupler, an advanced 2.5 A output current IGBT drive optocoupler, offers the critical protection necessary for preventing fault conditions that lead to destructive thermal runaway of IGBTs. Pin-for-pin compatible with current solutions, the FOD8316 consists of an integrated gate drive optocoupler featuring low  $R_{DS(ON)}$  CMOS transistors to drive the IGBT from rail-to-rail and high-speed isolated feedback circuitry for fault sensing. It is ideally suited for driving fast-switching power IGBTs and MOSFETs.

The FOD8316 offers best-in-class noise immunity, resulting from its proprietary Optoplanar® coplanar packaging technology. The optoplanar technology ensures safe insulation thickness of more than 0.4 millimeters in attaining reliable high-voltage isolation, certified by UL1577 and DIN EN/IEC60747-5-5 standards.




Figure 1. 3-Dimensional Illustration of the Internal Die Set of Fairchild's Optoplanar® Package Construction

### 1.1. Features and Benefits

- 2.5 A output current driving capability for most 1200 V / 150 A IGBTs
- High noise immunity characterized by CMR: 35 kV/ $\mu$ s at  $V_{cm} = 1500 V_{peak}$
- 1414  $V_{peak}$  working insulation voltage and 8000  $V_{peak}$  transient isolation voltage rating
- Output voltage swing rail-to-rail: low power dissipation
- Soft IGBT turn-off
- High speed: 500 ns propagation delay
- 3.3 V / 5V, CMOS/TTL-compatible inputs

## 1.2. Applications

- Motor Drives
- Industrial Inverters
- Solar Power Inverters
- Uninterruptible Power Supplies (UPS)
- Induction Heating
- Isolated IGBT Drive





Figure 2. FOD8316 Block Diagram

## 2. Operations


The application circuit and the timing diagram illustrate the functional use of the FOD8316 between a micro-controller and a three-phase system, as well as the interaction of the internal and external signals.



**Figure 3. Typical Application Circuit**

The internal gate driving circuitry of FOD8316 can be used with either a single positive power supply,  $V_{DD2}$ , or a dual positive and negative supply,  $V_{DD2}$  and  $V_{SS}$ . The output driver stage,  $V_O$ , is made up of a pair of PMOS and NMOS transistors, which facilitates close to rail-to-rail output swing. This allows a tight control of gate voltage during on-state and short-circuit condition. Due to the low  $R_{DS(ON)}$  of the MOSFETs, the power dissipation is reduced as compared to bipolar-type driver output stages. The absolute maximum rating of the output peak current,  $I_{O(PEAK)}$ , is 3 A.

FOD8316 provides short-circuit protection by means of desaturation-detection circuits that monitor the collector-emitter voltage of the IGBT. When the DESAT voltage increases above the threshold voltage, a short-circuit condition is detected and the driver output stage executes a “soft” IGBT turn-off and is eventually driven low. The soft turn-off feature ensures the safe turn-off of the IGBT under fault conditions. This reduces the voltage spike on the collector of the IGBT. Without this, the IGBT would see a heavy spike on the collector, resulting in a permanent damage to the device when it is turned off immediately. The FAULT open-drain output is triggered active LOW to report a desaturation error to the micro-controller. The FAULT signal is cleared by activating the RESET pin with an active LOW signal communicated by the external controller. The DESAT fault detector should be disabled for a short period (blanking time) before the IGBT turns on to allow the collector voltage to fall below the DESAT threshold. This blanking period protects against false trigger of the DESAT while the IGBT is turning on.



**Figure 4. Timing Diagram**

The FOD8316 is also designed with an under-voltage detection circuit to prevent the application of insufficient gate voltage to the IGBT. This could be dangerous, as it would drive the IGBT out of saturation and into the linear operation where the losses are very high and the device is quickly overheated.

### 3. Circuit Schematic

The FEBFOD8316 evaluation board with a booster circuit is designed for the evaluation of FOD8316 timing sequence and AC test performance when driving an IGBT power module. It is recommended to be used in conjunction with the datasheet.

The FOD8316 is designed to perform as a stand-alone, optically coupled, gate driver in most applications. If larger gate drive capability is needed for large IGBT modules or parallel operation, an output booster stage may be added to driver for optimum performance.

One possible implementation is by a discrete NPN/PNP totem-pole configuration. These booster transistors should be fast switching and have sufficient current gain to deliver the desired peak output current.





Figure 5. Circuit Schematic



**Figure 6. Photograph of the Board**

This board consists of a FOD8316 component, a non-inverting bipolar (NPN/PNP) totem-pole current buffer, two capacitor loads (10 nF/51 nF), as well as connectors and test terminals for power supplies and input signals.

The FOD8316 can be evaluated as a stand-alone gate driver driving a 10 nF capacitor load or FOD8316 with the totem-pole current buffer driving a 51 nF capacitor load.

## 4. Setup and Operation

The setup requires three power supply sources:  $V_{DD1}$  on one side of the isolation barrier,  $V_{DD2}$  (positive supply), and  $V_{SS}$  (negative supply using two power supplies) on the other side of the isolation barrier.

There are two CMOS/TTL-compatible inputs,  $V_{IN+}$  and  $V_{IN-}$ , to control the IGBT in non-inverting and inverting configurations, respectively. When  $V_{IN-}$  is set LOW,  $V_{IN+}$  controls the driver output,  $V_O$  in non-inverting configuration. When  $V_{IN+}$  is set HIGH,  $V_{IN-}$  controls the driver output in inverting configuration.

The subsequent sections describe the set up for non-inverting configuration, where  $V_{IN-}$  is connected to GND1.

The input signal is applied at the  $V_{IN+}$  and the resulting output is used to drive either a 10 nF capacitor load (C8) or a totem-pole current buffer, which in turn drives a bigger capacitor load (C12). Test points located at selected positions (as indicated in the schematics) allow the technician to probe out the signals and measure the switching characteristics of the device.

## 5. Test Procedures and Conditions

This section describes the default setup of the FEBFOD8316 evaluation board. Please refer to the schematic in Figure 5.

1. Connect the power supplies across the following connector:
  - Across  $V_{DD1}$  and GND1. Set the voltage to 5 V.
  - Across  $V_{DD2}$  and  $V_E$  (GND of the power supply). Set the voltage to 15 V.
  - Across  $V_E$  and  $V_{SS}$  (GND of the power supply). Set the voltage to 5 V.

This power supply configuration enables  $V_O$  to swing from  $-5$  V to 15 V.
2. Apply the following signal at  $V_{IN+}$ : 10 kHz, square wave, 50% duty cycle, amplitude = 5 V.
3. Evaluation can be completed with the FOD8316 as a standalone gate driver or together with the totem-pole current buffer. The jumper configurations are shown in Table 1 on the following page.
4. If soft turn-off evaluation is required, J13 must be left open, with no shorting jumper installed, and TP7 (Desat) has to be pulled above the desat threshold voltage.
5. Scope shots of the signals are shown in the following section using the board in standalone set up and with the totem-pole current buffer.
6. Additional evaluation is accomplished by changing the jumper configuration. For example, the board can be configured to positive gate drive ( $V_O > 0$  V), only requiring one power supply source at each side of the isolation barrier. The desat threshold voltage (seen at TP7) and the blanking time, can also be varied using jumper J10 and by soldering additional capacitor on the C9 pads.
7. The test points and their corresponding signals are listed in Table 2 on the next page.

**Table 1. EVB Jumper Configurations**

| Configuration   | J1 | J2 | J3 | J4* | J5 | J6 | J7 | J8 | J9 | J10 | J11 | J12 | J13 | J14 | J15 |
|---|----|----|----|-----|----|----|----|----|----|-----|-----|-----|-----|-----|-----|
| Vo swing = 5 V to 15 V;<br>FOD8316 standalone                                       | X  |    |    |     | X  |    |    |    |    | X   |     |     | X   | X   |     |
| Vo swing = 5 V to 15 V;<br>FOD8316 + totem-pole                                     | X  |    |    |     | X  |    | X  | X  | X  | X   |     |     | X   | X   | X   |
| Vo swing = 5 V to 15 V;<br>FOD8316 and totem pole<br>(for soft turn-off evaluation) | X  |    |    |     | X  |    | X  | X  | X  | X   |     |     |     | X   | X   |
| Vo swing = 5 V to 15 V;<br>FOD8316 standalone<br>(for soft turn-off evaluation)     | X  |    |    |     | X  |    |    |    |    | X   |     |     |     | X   |     |

X = jumper short, blank = jumper open

\*J4 is removed in the latest revision of the evaluation board.

**Table 2. Test Points**

| Test Point | Description  |
|------------|--|
| TP1        | $V_{IN+}$ , non-inverting gate drive control input       |
| TP1A       | $V_{IN-}$ , inverting gate drive control input           |
| TP2        | $V_{DD1}$ , positive input supply voltage (3 V to 5.5 V) |
| TP3        | $\overline{RESET}$ , FAULT reset input                   |
| TP4        | $\overline{FAULT}$ , fault output                        |
| TP5/5A     | $V_{LED1-}$ , LED1 cathode (must be connected to ground) |
| TP6/6A/6B  | $V_E$ , output supply voltage/IGBT emitter               |
| TP7        | DESAT, desaturation voltage input                        |
| TP8        | $V_{DD2}$ , positive output supply voltage               |
| TP9        | $V_S$ , source of pull-up PMOS transistor                |
| TP10       | $V_{O1}$ , gate drive output voltage                     |
| TP11       | $V_{O2}$ , totem pole current buffer output voltage      |
| TP12       | $V_{SS}$ , negative output supply voltage                |

## 6. Scope Shots




Figure 7. FOD8316  $V_{IN+}$  and  $V_{O1}$  Waveform in Standalone Configuration




Figure 8. FOD8316  $V_{IN+}$  and  $V_{O1}$  Waveform in Standalone Configuration During Soft Turn-Off




Figure 9. FOD8316  $V_{IN+}$ ,  $V_{O1}$  and  $V_{O2}$  Waveform




Figure 10. FOD8316  $V_{IN+}$ ,  $V_{O1}$  and  $V_{O2}$  Waveform During Soft Turn-Off

## 7. Conclusion

The FEDFOD8316 evaluation board allows the user to quickly evaluate the performance of the Fairchild Semiconductor's FOD8316 smart gate driver optocoupler.

Measurement results clearly demonstrate the AC performance and critical protection features of the product that are needed during IGBT fault conditions. With proper booster circuit design, the gate drive capability can be enhanced without affecting key features, such as desaturation detection and soft turn-off timings.



## 8. Revision History

| Rev.  | Date         | Description     |
|-------|--------------|-----------------|
| 1.0.0 | January 2013 | Initial Release |
|       |              |                 |
|       |              |                 |
|       |              |                 |

---

### WARNING AND DISCLAIMER

Replace components on the Evaluation Board only with those parts shown on the parts list (or Bill of Materials) in the Users' Guide. Contact an authorized Fairchild representative with any questions.

This board is intended to be used by certified professionals, in a lab environment, following proper safety procedures. Use at your own risk. The Evaluation board (or kit) is for demonstration purposes only and neither the Board nor this User's Guide constitute a sales contract or create any kind of warranty, whether express or implied, as to the applications or products involved. Fairchild warrants that its products meet Fairchild's published specifications, but does not guarantee that its products work in any specific application. Fairchild reserves the right to make changes without notice to any products described herein to improve reliability, function, or design. Either the applicable sales contract signed by Fairchild and Buyer or, if no contract exists, Fairchild's standard Terms and Conditions on the back of Fairchild invoices, govern the terms of sale of the products described herein.

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

#### LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

---

### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, [www.fairchildsemi.com](http://www.fairchildsemi.com), under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

---

### EXPORT COMPLIANCE STATEMENT

These commodities, technology, or software were exported from the United States in accordance with the Export Administration Regulations for the ultimate destination listed on the commercial invoice. Diversion contrary to U.S. law is prohibited.

U.S. origin products and products made with U.S. origin technology are subject to U.S. Re-export laws. In the event of re-export, the user will be responsible to ensure the appropriate U.S. export regulations are followed.

ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## PUBLICATION ORDERING INFORMATION

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor  
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA  
**Phone:** 303-675-2175 or 800-344-3860 Toll Free USA/Canada  
**Fax:** 303-675-2176 or 800-344-3867 Toll Free USA/Canada  
**Email:** [orderlit@onsemi.com](mailto:orderlit@onsemi.com)

**N. American Technical Support:** 800-282-9855 Toll Free  
USA/Canada  
**Europe, Middle East and Africa Technical Support:**  
Phone: 421 33 790 2910  
**Japan Customer Focus Center**  
Phone: 81-3-5817-1050

**ON Semiconductor Website:** [www.onsemi.com](http://www.onsemi.com)  
**Order Literature:** <http://www.onsemi.com/orderlit>  
For additional information, please contact your local  
Sales Representative