



ON Semiconductor®

CPH3456

SPICE PARAMETER

Nch MOS FET

model : BSIM3V3.2

Parameter	Value	Parameter	Value	Parameter	Value
LEVEL	8				
VERSION	3.2	TNOM	27	TOX	3.3E-08
VTH0	0.94	K1	1.96	K2	-0.04
NLX	1.70E-07	DVT0	3.12	DVT1	0.58
DVT2	-0.01	U0	630	UA	2.20E-09
UB	1.00E-21	VSAT	1.75E+05	A0	0.32
AGS	-0.88	A1	0	A2	1
RDSW	1.58E+03	PRWG	-8.00E-03	WR	0.82
WINT	0	LINT	6.00E-08	VOFF	-0.13
NFACTOR	0.7	CIT	0	CDSC	2.40E-04
CDSCD	0	ETA0	0.12	DSUB	0.96
PCLM	0.8	PDIBLC1	0	PDIBLC2	1.00E-05
DROUT	0.96	PSCBE1	7.00E+08	PSCBE2	9.55E-08
PVAG	0.01	DELTA	0.05	NGATE	1.00E+19
MOBMOD	1	NQSMOD	0	NOIMOD	1
CAPMOD	3	XPART	0.5	CGSO	1.00E-12
CGDO	2.00E-11	CGBO	0	CGSL	0
CGDL	5.70E-10	CKAPPA	1.2	CF	0
CLC	3.00E-09	CLE	0.8	DWC	0
DLC	-1.00E-12	NOFF	3.66	VOFFCV	-0.4
ACDE	1	MOIN	15	CJ	1.50E-04
MJ	0.45	PB	0.6	JS	8.00E-07
NJ	1.05	XTI	3	IJTH	0
KT1	-0.4	UTE	-0.3	PRT	2.80E+03
AT	3.30E+04				

Temp = 27 deg
 L = 1.0E-6 m
 W = 384307E-6 m
 AD = 384307E-12 m²
 RG = 16 ohm
 RB = 0.03 ohm

Date : 2010/11/19

*Information herein is for example only ;
 It is not guaranteed for volume production.

ON Semiconductor

